

LVDS 4x4 CROSSPOINT SWITCH

FEATURES

- **Signaling Rates >1.5 Gbps per Channel**
- **Supports Telecom/Datacom and HDTV Video Switching**
- **Non-Blocking Architecture Allows Each Output to be Connected to Any Input**
- **Compatible With ANSI TIA/EIA-644-A LVDS Standard**
- **25 mV of Input Voltage Threshold Hysteresis**
- **Propagation Delay Times, 900 ps Typical**
- **Inputs Electrically Compatible With LVPECL, CML and LVDS Signal Levels**
- **Operates From a Single 3.3-V Supply**
- **Integrated 110-Ω Line Termination Resistors Available With SN65LVDT125**

APPLICATIONS

- **Clock Buffering / Clock Muxing**
- **Wireless Base Stations**
- **High-Speed Network Routing**
- **HDTV Video Switching**


DESCRIPTION

The SN65LVDS125 and SN65LVDT125 are 4x4 nonblocking crosspoint switches. Low-voltage differential signaling (LVDS) is used to achieve signaling rates of 1.5 Gbps per channel. Each output driver includes a 4:1 multiplexer to allow any input to be routed to any output. Internal signal paths are fully differential to achieve the high signaling speeds while maintaining low signal skews. The SN65LVDT125 incorporates 110-Ω termination resistors for those applications where board space is a premium.


Designed to support signaling rates up to 1.5 Gbps for OC-12 clocks (622 MHz). The 1.5-Gbps signaling rate allows use in HDTV systems, including SMPTE 292 video applications requiring signaling rates of 1.485 Gbps.

The SN65LVDS125 and SN65LVDT125 are characterized for operation from −40°C to 85°C.

SN65LVDS125DBT (Marked as LVDS125)
SN65LVDT125DBT (Marked as LVDT125)
(TOP VIEW)



Eye Pattern of Two Outputs Operating Simultaneously




Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

PRODUCTION DATA information is current as of publication date. Products conform to specifications per the terms of Texas Instruments standard warranty. Production processing does not necessarily include testing of all parameters.

Copyright © 2002–2004, Texas Instruments Incorporated

These devices have limited built-in ESD protection. The leads should be shorted together or the device placed in conductive foam during storage or handling to prevent electrostatic damage to the MOS gates.


LOGIC DIAGRAM




Integrated 110-Ω Termination on LVDT Only

EQUIVALENT INPUT AND OUTPUT SCHEMATIC DIAGRAMS

INPUT LVDS125



OUTPUT LVDS125



CROSSPOINT LOGIC TABLES

OUTPUT CHANNEL 1			OUTPUT CHANNEL 2			OUTPUT CHANNEL 3			OUTPUT CHANNEL 4		
CONTROL PINS		INPUT SELECTED	CONTROL PINS		INPUT SELECTED	CONTROL PINS		INPUT SELECTED	CONTROL PINS		INPUT SELECTED
S10	S11	1Y/1Z	S20	S21	2Y/2Z	S30	S31	3Y/3Z	S40	S41	4Y/4Z
0	0	1A/1B	0	0	1A/1B	0	0	1A/1B	0	0	1A/1B
0	1	2A/2B	0	1	2A/2B	0	1	2A/2B	0	1	2A/2B
1	0	3A/3B	1	0	3A/3B	1	0	3A/3B	1	0	3A/3B
1	1	4A/4B	1	1	4A/4B	1	1	4A/4B	1	1	4A/4B

PACKAGE DISSIPATION RATINGS

PACKAGE	CIRCUIT BOARD MODEL	$T_A \leq 25°C$ POWER RATING	DERATING FACTOR(1) ABOVE $T_A = 25°C$	$T_A = 85°C$ POWER RATING
TSSOP (DBT)	High−K(2)	1772 mW	15.4 mW/°C	847 mW

(1) This is the inverse of the junction-to-ambient thermal resistance when board-mounded and with no air flow.
(2) In accordance with the High−K thermal metric definitions of EIA/JESD51−6

THERMAL CHARACTERISTICS

PARAMETER			TEST CONDITIONS	VALUE	UNITS
θ_{JB}	Junction-to-board thermal resistance			40.3	°C/W
θ_{JC}	Junction-to-case thermal resistance			8.5	
P_D	Device power dissipation	Typical	V_{CC} = 3.3 V, T_A = 25°C, 750 MHZ	356	mW
		Maximum	V_{CC} = 3.6 V, T_A = 85°C, 750 MHZ	522	mW

ABSOLUTE MAXIMUM RATINGS

over operating free-air temperature range unless otherwise noted(1)

			UNITS
Supply voltage range, v_{CC}			−0.5 V to 4 V
Voltage range	S, DE		−0.5 V to 4 V
	(A, B)		−0.5 V to 4 V
	$\lvert V_A - V_B \rvert$ (LVDT only)		1 V
	(Y, Z)		−0.5 V to 4 V
Electrostatic discharge	Human body model(3)	All pins	±3 kV
	Charged-device model(4)	All pins	±500 V
Continuous power dissipation			See Dissipation Rating Table
Storage temperature range			−65°C to 150°C

(1) Stresses beyond those listed under “absolute maximum ratings” may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under “recommended operating conditions” is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.
(2) All voltage values, except differential I/O bus voltages, are with respect to network ground terminal.
(3) Tested in accordance with JEDEC Standard 22, Test Method A114-A.
(4) Tested in accordance with JEDEC Standard 22, Test Method C101.

RECOMMENDED OPERATING CONDITIONS

		MIN	NOM	MAX	UNIT
Supply voltage, V_{CC}		3	3.3	3.6	V
High-level input voltage, V_{IH}	S10−S41, 1DE−4DE	2			V
Low-level input voltage, V_{IL}	S10−S41, 1DE−4DE			0.8	V
Magnitude of differential input voltage $\|V_{ID}\|$	LVDS	0.1			V
	LVDT	0.1		0.8	V
Input voltage (any combination of common−mode or input signals)		0		3.3	V
Junction temperature, T_J				140	°C
Operating free-air temperature, T_A (1)		−40		85	°C

(1) Maximum free-air temperature operation is allowed as long as the device maximum junction temperature is not exceeded.

TIMING SPECIFICATIONS

PARAMETER			MIN	NOM	MAX	UNIT
t_{SET}	Input to select setup time	See Figure 7		0.6		ns
t_{HOLD}	Input to select hold time			0.2		ns
t_{SWITCH}	Select to switch output			1.2	1.6	ns

INPUT ELECTRICAL CHARACTERISTICS

over recommended operating conditions unless otherwise noted(1)

PARAMETER			TEST CONDITIONS	MIN	TYP(1)	MAX	UNIT
V_{IT+}	Positive-going differential input voltage threshold		See Figure 1			100	mV
$V_{IT−}$	Negative-going differential input voltage threshold		See Figure 1	−100			mV
$V_{ID(HYS)}$	Differential input voltage hysteresis				25		mV
I_{IH}	High-level input current	1DE−4DE	V_{IH} = 2 V			−10	µA
		S10−S41				20	
I_{IL}	Low-level input current	1DE−4DE	V_{IL} = 0.8 V			−10	µA
		S10−S41				20	
I_I	Input current		V_I = 0 V or 3.3 V, second input at 1.2 V (other input open for LVDT)	−20		20	µA
$I_{I(OFF)}$	Input current		$V_{CC} \le 1.5$ V, V_I = 0 V or 3.3 V, second input at 1.2 V (other input open for LVDT)	−20		20	µA
I_{IO}	Input offset current ($\|I_{IA} − I_{IB}\|$) ('LVDS)		$V_{IA} = V_{IB}$, $0 \le V_{IA} \le 3.3$ V	−6		6	µA
R_T	Termination resistance ('LVDT)		V_{ID} = 300 mV, V_{IC}= 0 V to 3.3 V	90	110	132	Ω
	Termination resistance('LVDT with power-off)		V_{ID} = 300 mV, V_{IC}= 0 V to 3.3 V, V_{CC} = 1.5 V	90	110	132	
C_T	Differential input capacitance				0.6		pF

(1) All typical values are at 25°C and with a 3.3 V supply.

OUTPUT ELECTRICAL CHARACTERISTICS

over recommended operating conditions unless otherwise noted(1)

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
$\|V_{OD}\|$	Differential output voltage magnitude	See Figure 2	247	350	454	mV
$\Delta\|V_{OD}\|$	Change in differential output voltage magnitude between logic states	V_{ID} = ±100 mV	−50		50	mV
$V_{OC(SS)}$	Steady-state common-mode output voltage	See Figure 3	1.125		1.375	V
$\Delta V_{OC(SS)}$	Change in steady-state common-mode output voltage between logic states		−50		50	mV
$V_{OC(PP)}$	Peak-to-peak common-mode output voltage			50	150	mV
I_{CC}	Supply current	R_L=100Ω, C_L = 1 pF		107	145	mA
I_{OS}	Short-circuit output current	V_{OY} or V_{OZ} = 0 V	−27		27	mA
I_{OSD}	Differential short circuit output current	V_{OD} = 0 V	−12		12	mA
I_{OZ}	High-impedance output current	V_O = 0 V or V_{CC}	−1		±1	µA
C_O	Differential output capacitance			1.2		pF

SWITCHING CHARACTERISTICS

over recommended operating conditions unless otherwise noted(1)

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
t_{PLH}	Propagation delay time, low-to-high-level output	See Figure 4	700	900	1200	ps
t_{PHL}	Propagation delay time, high-to-low-level output		700	900	1200	
t_r	Differential output signal rise time (20%−80%)			210	255	
t_f	Differential output signal fall time (20%−80%)			210	255	
$t_{sk(p)}$	Pulse skew ($\|t_{PHL} - t_{PLH}\|$)(1)			0	50	ps
$t_{sk(o)}$	Channel-to-channel output skew(2)				150	ps
$t_{sk(pp)}$	Part-to-part skew(3)				300	ps
$t_{jit(per)}$	Period jitter, rms (1 standard deviation)(4)	750 MHz clock input(5) (see Figure 6)		0.4	3	ps
$t_{jit(cc)}$	Cycle-to-cycle jitter (peak)(4)	750 MHz clock input(6) (see Figure 6)		4.7	13	ps
$t_{jit(pp)}$	Peak-to-peak jitter(4)	1.5 Gbps 2^{23}−1 PRBS input(7) (see Figure 6)		65	110	ps
$t_{jit(det)}$	Deterministic jitter, peak-to-peak(4)	1.5 Gbps 2^7−1 PRBS input(8) (see Figure 6)		56	90	ps
t_{PHZ}	Propagation delay, high-level-to−high-impedance output	See Figure 5			6	ns
t_{PLZ}	Propagation delay, low-level-to-high-impedance output				6	
t_{PZH}	Propagation delay, high-impedance -to-high-level output				50	
t_{PZL}	Propagation delay, high-impedance-to-low-level output				50	

(1) $t_{sk(p)}$ is the magnitude of the time difference between the t_{PLH} and t_{PHL} of any output of a single device.
(2) $t_{sk(o)}$ is the maximum delay time difference between drivers over temperature, V_{CC}, and process.
(3) $t_{sk(pp)}$ is the magnitude of the difference in propagation delay times between any specified terminals of two devices when both devices operate with the same supply voltages, at the same temperature, and have identical packages and test circuits.
(4) Jitter specifications are based on design and characteriztion. Stimulus system jitter of 1.9 ps $t_{jit(per)}$, 16 ps $t_{jit(cc)}$. 17 ps $t_{jit(pp)}$, and 7.2 ps $t_{jit(det)}$ have been subtracted from the values.
(5) Input voltage = V_{ID} = 200 mV, 50% duty cycle at 750 MHz, t_r = t_f = 50 ps (20% to 80%), measured over 1000 samples.
(6) Input voltage = V_{ID} = 200 mV, 50% duty cycle at 750 MHz, t_r = t_f = 50 ps (20% to 80%).
(7) Input voltage = V_{ID} = 200 mV, 2^{23}−1 PRBS pattern at 1.5 Gbps, t_r = t_f = 50 ps (20% to 80%), measured over 200k samples.
(8) Input voltage = V_{ID} = 200 mV, 2^7−1 PRBS pattern at 1.5 Gbps, t_r = t_f = 50 ps (20% to 80%).

PARAMETER MEASUREMENT INFORMATION




Figure 1. Voltage and Current Definitions






Figure 2. Differential Output Voltage (V_{OD}) Test Circuit




NOTE: All input pulses are supplied by a generator having the following characteristics: t_r or $t_f \le 1$ ns, pulse-repetition rate (PRR) = 0.5 Mpps, pulse width = 500 ±10 ns; R_L = 100W; C_L includes instrumentation and fixture capacitance within 0,06 mm of the D.U.T.;the measurement of $V_{OC(PP)}$ is made on test equipment with a −3 dB bandwidth of at least 300 MHz.

Figure 3. Test Circuit and Definitions fot the Driver Common-Mode Output Voltage




NOTE: All input pulses are supplied by a generator having the following characteristics: t_r or $t_f \le .25$ ns, pulse-repetition rate (PRR) = 0.5 Mpps, pulse width = 500 ± 10 ns . C_L includes instrumentation and fixture capacitance within 0,06 mm of the D.U.T.

Figure 4. Timing Test Circuit and Waveforms




NOTE: A. All input pulses are supplied by a generator having the following characteristics: t_r or $t_f \le 1$ ns, pulse-repetition rate (PRR) = 0.5 Mpps, pulse width = 500 ± 10 ns . C_L includes instrumentation and fixture capacitance within 0,06 mm of the D.U.T.

Figure 5. Enable and Disable Time Circuit and Definitions



NOTE: A. All input pulses are supplied by an Agilent 81250 Stimulus System.
NOTE: B. The measurement is made on a TEK TDS6604 running TDSJIT3 application software.

Figure 6. Driver Jitter Measurement Waveforms



NOTE: t_{SET} and t_{HOLD} times specify that data must be in a stable state before and after mux control switches.

Figure 7. Input to Select for Both Rising and Falling Edge Setup and Hold Times

TYPICAL CHARACTERISTICS

SUPPLY CURRENT vs FREQUENCY




Figure 8

PROPAGATION DELAY TIME vs FREE-AIR TEMPERATURE




Figure 9

PROPAGATION DELAY TIME vs COMMON-MODE INPUT VOLTAGE




Figure 10

PEAK-TO-PEAK JITTER vs FREQUENCY




Figure 11

PEAK-TO-PEAK JITTER vs DATA RATE




Figure 12

PEAK-TO-PEAK JITTER vs FREQUENCY




Figure 13

PEAK-TO-PEAK JITTER vs DATA RATE




Figure 14

PEAK-TO-PEAK JITTER vs FREQUENCY




Figure 15

PEAK-TO-PEAK JITTER vs DATA RATE




Figure 16

PEAK-TO-PEAK JITTER vs FREE-AIR TEMPERATURE




Figure 17

PEAK-TO-PEAK JITTER vs DATA RATE




Figure 18

DIFFERENTIAL OUTPUT VOLTAGE vs FREQUENCY





Figure 19


APPLICATION INFORMATION

CONFIGURATION EXAMPLES


S10	S11	S20	S21
0	0	0	1
S30	S31	S40	S41
1	0	1	1




S10	S11	S20	S21
0	0	0	0
S30	S31	S40	S41
0	0	0	0



S10	S11	S20	S21
0	0	0	0
S30	S31	S40	S41
1	0	1	0



S10	S11	S20	S21
1	1	1	1
S30	S31	S40	S41
0	0	0	0



APPLICATION INFORMATION

TYPICAL APPLICATION CIRCUITS (ECL, PECL, LVDS, ETC.)




Figure 20. Low-Voltage Positive Emitter-Coupled Logic (LVPECL)




Figure 21. Current-Mode Logic (CML)




Figure 22. Single-Ended (LVPECL)





Figure 23. Low-Voltage Differential Signaling (LVDS)

DBT (R-PDSO-G**)

PLASTIC SMALL-OUTLINE PACKAGE

30 PINS SHOWN



DIM \ PINS **	20	24	28	30	38	44	50
A MAX	5,10	6,60	7,90	7,90	9,80	11,10	12,60
A MIN	4.90	6,40	7,70	7,70	9,60	10,90	12,40

4073252/E 02/02

NOTES: A. All linear dimensions are in millimeters.
B. This drawing is subject to change without notice.
C. Body dimensions do not include mold flash or protrusion.
D. Falls within JEDEC MO-153

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products		**Applications**	
Amplifiers	amplifier.ti.com	Audio	www.ti.com/audio
Data Converters	dataconverter.ti.com	Automotive	www.ti.com/automotive
DSP	dsp.ti.com	Broadband	www.ti.com/broadband
Interface	interface.ti.com	Digital Control	www.ti.com/digitalcontrol
Logic	logic.ti.com	Military	www.ti.com/military
Power Mgmt	power.ti.com	Optical Networking	www.ti.com/opticalnetwork
Microcontrollers	microcontroller.ti.com	Security	www.ti.com/security
		Telephony	www.ti.com/telephony
		Video & Imaging	www.ti.com/video
		Wireless	www.ti.com/wireless

Mailing Address: Texas Instruments
Post Office Box 655303 Dallas, Texas 75265

Copyright © 2004, Texas Instruments Incorporated