TPS3600D20, TPS3600D25, TPS3600D33, TPS3600D50
BATTERY-BACKUP SUPERVISORS FOR LOW-POWER PROCESSORS


features

- Supply Current of 40 μA (Max)
- Precision Supply Voltage Monitor
  - 2.0 V, 2.5 V, 3.3 V, 5.0 V
  - Other Versions on Request
- Watchdog Timer With 800-ms Time-Out
- Backup-Battery Voltage Can Exceed V_{DD}
- Power-On Reset Generator With Fixed 100-ms Reset Delay Time
- Battery OK Output
- Voltage Monitor for Power-Fail or Low-Battery Monitoring
- Manual Switchover to Battery-Backup Mode
- Chip-Enable Gating −3 ns (at V_{DD} = 5 V) Max. Propagation Delay
- Manual Reset
- Battery Freshness Seal
- 14-Pin TSSOP Package
- Temperature Range . . . −40°C to 85°C

typical applications

- Fax Machines
- Set-Top Boxes
- Advanced Voice Mail Systems
- Portable Battery Powered Equipment
- Computer Equipment
- Advanced Modems
- Automotive Systems
- Portable Long-Time Monitoring Equipment
- Point of Sale Equipment


TSSOP (PW) Package
(TOP VIEW)





ACTUAL SIZE
(5,10mm x 6,60mm)

typical operating circuit



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

All trademarks are the property of their respective owners.

PRODUCTION DATA information is current as of publication date. Products conform to specifications per the terms of Texas Instruments standard warranty. Production processing does not necessarily include testing of all parameters.

Copyright © 2000−2007, Texas Instruments Incorporated

description

The TPS3600 family of supervisory circuits monitor and control processor activity. In case of power-fail or brownout conditions, the backup-battery switchover function of TPS3600 allows to run a low-power processor and its peripherals from the installed backup battery without asserting a reset beforehand.


During power on, $\overline{\text{RESET}}$ is asserted when the supply voltage (V_{DD} or V_{BAT}) becomes higher than V_{res}. Thereafter, the supply voltage supervisor monitors V_{OUT} and keeps $\overline{\text{RESET}}$ output active as long as V_{OUT} remains below the threshold voltage (V_{IT}). An internal timer delays the return of the output to the inactive state (high) to ensure proper system reset. This delay timer starts its time-out, after V_{OUT} has risen above the threshold voltage (V_{IT}). In case of a brownout or power failure of both supply sources, a voltage drop below the threshold voltage (V_{IT}) get detected and the output becomes active (low) again.

The product spectrum is designed for supply voltages of 2 V, 2.5 V, 3.3 V, and 5 V. The circuits are available in a 14-pin TSSOP package. They are characterized for operation over a temperature range of −40°C to 85°C.

PACKAGE INFORMATION

T_A	DEVICE NAME
−40°C to 85°C	TPS3600D20
	TPS3600D25
	TPS3600D33
	TPS3600D50

ordering information application specific versions (see Note)



DEVICE NAME	NOMINAL VOLTAGE, V_{NOM}
TPS3600x20 PW	2.0 V
TPS3600x25 PW	2.5 V
TPS3600x33 PW	3.3 V
TPS3600x50 PW	5.0 V

DEVICE NAME	NOMINAL BATTOK THRESHOLD VOLTAGE, V_{BOK}
TPS3600Dxx PW	V_{IT} + 7%
TPS3600Fxx PW†	V_{IT} + 6%
TPS3600Hxx PW†	V_{IT} + 8%
TPS3600Jxx PW†	V_{IT} + 10%

† For the application specific versions, please contact the local TI sales office for availability and lead time.

FUNCTION TABLES

$V_{DD} > V_{SW}$	$V_{OUT} > V_{IT}$	$V_{DD} > V_{BAT}$	MSWITCH	$\overline{MR}$	V_{OUT}	BATTON	$\overline{RESET}$	$\overline{CEOUT}$
0	0	0	0	0	V_{BAT}	1	0	DIS
0	0	0	0	1	V_{BAT}	1	0	DIS
0	0	0	1	0	V_{BAT}	1	0	DIS
0	0	0	1	1	V_{BAT}	1	0	DIS
0	0	1	0	0	V_{DD}	0	0	DIS
0	0	1	0	1	V_{DD}	0	0	DIS
0	0	1	1	0	V_{BAT}	1	0	DIS
0	0	1	1	1	V_{BAT}	1	0	DIS
0	1	0	0	0	V_{BAT}	1	0	DIS
0	1	0	0	1	V_{BAT}	1	1	EN
0	1	0	1	0	V_{BAT}	1	0	DIS
0	1	0	1	1	V_{BAT}	1	1	EN
0	1	1	0	0	V_{DD}	0	0	DIS
0	1	1	0	1	V_{DD}	0	1	EN
0	1	1	1	0	V_{BAT}	1	0	DIS
0	1	1	1	1	V_{BAT}	1	1	EN
1	1	0	0	0	V_{DD}	0	0	DIS
1	1	0	0	1	V_{DD}	0	1	EN
1	1	0	1	0	V_{BAT}	1	0	DIS
1	1	0	1	1	V_{BAT}	1	1	EN
1	1	1	0	0	V_{DD}	0	0	DIS
1	1	1	0	1	V_{DD}	0	1	EN
1	1	1	1	0	V_{BAT}	1	0	DIS
1	1	1	1	1	V_{BAT}	1	1	EN

$V_{BAT} > V_{BOK}$	BATTOK
0	0
1	1

CONDITION: $V_{OUT} > V_{DD(min)}$


$\overline{CEIN}$	$\overline{CEOUT}$
0	0
1	1

CONDITION: Enabled


PFI > V_{PFI}	$\overline{PFO}$
0	0
1	1

CONDITION: $V_{OUT} > V_{DD(min)}$

functional schematic



timing diagram



NOTES: A. MSWITCH = 0, $\overline{MR}$ = 1
NOTES: B. Timing diagram shown under normal operation, not in freshness seal mode.

Terminal Functions

TERMINAL NAME	TERMINAL NO.	I/O	DESCRIPTION
BATTOK	9	O	Battery status output
BATTON	6	O	Logic output/external bypass switch driver output
$\overline{\text{CEIN}}$	5	I	Chip-enable input
$\overline{\text{CEOUT}}$	10	O	Chip-enable output
GND	3	I	Ground
$\overline{\text{MR}}$	11	I	Manual reset input
MSWITCH	4	I	Manual switch to force device into battery-backup mode (connect to GND if not used)
PFI	7	I	Power-fail comparator input (connect to GND if not used)
$\overline{\text{PFO}}$	8	O	Power-fail comparator output
$\overline{\text{RESET}}$	13	O	Active-low reset output
V_{BAT}	14	I	Backup-battery input
V_{DD}	2	I	Input supply voltage
V_{OUT}	1	O	Supply output
WDI	12	I	Watchdog timer input

detailed description

battery freshness seal

The battery freshness seal of the TPS3600 family disconnects the backup battery from the internal circuitry until it is needed. This ensures that the backup battery connected to V_{BAT} should be fresh when the final product is put to use. The following steps explain how to enable the freshness seal mode:

1. Connect V_{BAT} ($V_{BAT} > V_{BAT(min)}$)
2. Ground $\overline{\text{PFO}}$
3. Connect PFI to V_{DD} or PFI > $V_{(PFI)}$
4. Connect V_{DD} to power supply ($V_{DD} > V_{IT}$)
5. Ground $\overline{\text{MR}}$
6. Power down V_{DD}
7. The freshness seal mode is entered and pins $\overline{\text{PFO}}$ and $\overline{\text{MR}}$ can be disconnected.

The battery freshness seal mode is disabled by the positive-going edge of $\overline{\text{RESET}}$ when V_{DD} is applied.

BATTOK output

This is a logic feedback of the device to indicate the status of the backup battery. The supervisor checks the battery voltage every 200 ms with a voltage divider load of approximately 100 KΩ and a measure cycle on-time of 25 μs. This measurement cycle starts after the reset is released. If the battery voltage V_{BAT} is below the negative-going threshold voltage $V_{(BOK)}$, the indicator BATTOK does a high-to-low transition. Otherwise, its status remains to the V_{OUT} level.

Table 1. Typical Values for BATTOK Indication

SUPERVISOR TYPE	V_{IT} TYP	V_{BOK} MIN	V_{BOK} TYP	V_{BOK} MAX
TPS3600D20	1.78 V	1.84 V	1.91 V	1.97 V
TPS3600D25	2.22 V	2.3 V	2.38 V	2.46 V
TPS3600D33	2.93 V	3.04 V	3.14 V	3.24 V
TPS3600D50	4.40 V	4.56 V	4.71 V	4.86 V

detailed description (continued)




Figure 1. BATTOK Timing

chip-enable signal gating

The internal gating of chip-enable signals (CE) prevents erroneous data from corrupting CMOS RAM during an under-voltage condition. The TPS3600 use a series transmission gate from $\overline{\text{CEIN}}$ to $\overline{\text{CEOUT}}$. During normal operation (reset not asserted), the CE transmission gate is enabled and passes all CE transitions. When reset is asserted, this path becomes disabled, preventing erroneous data from corrupting the CMOS RAM. The short CE propagation delay from $\overline{\text{CEIN}}$ to $\overline{\text{CEOUT}}$ enables the TPS3600 devices to be used with most processors.

The CE transmission gate is disabled and $\overline{\text{CEIN}}$ is high impedance (disable mode) while reset is asserted. During a power-down sequence when V_{DD} crosses the reset threshold, the CE transmission gate will be disabled and $\overline{\text{CEIN}}$ immediately becomes high impedance if the voltage at $\overline{\text{CEIN}}$ is high. If $\overline{\text{CEIN}}$ is low during reset is asserted, the CE transmission gate will be disabled same time when $\overline{\text{CEIN}}$ goes high, or 15 μs after reset asserts, whichever occurs first. This will allow the current write cycle to complete during power down. When the CE transmission gate is enabled, the impedance of $\overline{\text{CEIN}}$ appears as a resistor in series with the load at $\overline{\text{CEOUT}}$. The overall device propagation delay through the CE transmission gate depends on V_{OUT}, the source impedance of the device connected to $\overline{\text{CEIN}}$ and the load at $\overline{\text{CEOUT}}$. To achieve minimum propagation delay, the capacitive load at $\overline{\text{CEOUT}}$ should be minimized, and a low-output-impedance driver be used.

During disable mode, the transmission gate is off and an active pullup connects $\overline{\text{CEOUT}}$ to V_{OUT}. This pullup turns off when the transmission gate is enabled.




Figure 2. Chip-Enable Timing

detailed description (continued)

power-fail comparator (PFI and $\overline{PFO}$)

An additional comparator is provided to monitor voltages other than the nominal supply voltage. The power-fail input (PFI) will be compared with an internal voltage reference of 1.15 V. If the input voltage falls below the power-fail threshold, $V_{(PFI)}$, of 1.15 V typical, the power-fail output ($\overline{PFO}$) goes low. If it goes above $V_{(PFI)}$ plus about 12-mV hysteresis, the output returns to high. By connecting two external resistors, it is possible to supervise any voltages above $V_{(PFI)}$. The sum of both resistors should be about 1 MΩ, to minimize power consumption and also to ensure that the current in the PFI pin can be neglected compared with the current through the resistor network. The tolerance of the external resistors should be not more than 1% to ensure minimal variation of sensed voltage.

If the power-fail comparator is unused, connect PFI to ground and leave $\overline{PFO}$ unconnected.

BATTON

Most often BATTON is used as a gate drive for an external pass transistor for high-current applications. In addition it can be also used as a logic output to indicate the battery switchover status. BATTON is high when V_{OUT} is connected to V_{BAT}.

BATTON can be directly connected to the gate of a PMOS transistor (see Figure 3). No current-limiting resistor is required. When using a PMOS transistor, it must be connected backwards from the traditional method (see Figure 3). This method orients the body diode from V_{DD} to V_{OUT} and prevents the backup battery from discharging through the FET when its gate is high.




Figure 3. Driving an External MOSFET Transistor With BATTON

backup-battery switchover

In the event of a brownout or power failure, it may be necessary to keep a processor running. If a backup battery is installed at V_{BAT}, the devices automatically connect the processor to backup power when V_{DD} fails. In order to allow the backup battery (e.g., a 3.6-V lithium cell) to have a higher voltage than V_{DD}, this family of supervisors will not connect V_{BAT} to V_{OUT} when V_{BAT} is greater than V_{DD}. V_{BAT} only connects to V_{OUT} (through a 2-Ω switch) when V_{OUT} falls below $V_{(SWN)}$ and V_{BAT} is greater than V_{DD}. When V_{DD} recovers, switchover is deferred either until V_{DD} crosses V_{BAT}, or when V_{DD} rises above the threshold $V_{(SWP)}$. (See the timing diagram)

$V_{DD} > V_{BAT}$	$V_{DD} > V_{(SW)}$	V_{OUT}
1	1	V_{DD}
1	0	V_{DD}
0	1	V_{DD}
0	0	V_{BAT}

detailed description (continued)

manual switchover (MSWITCH)

While operating in the normal mode from V_{DD}, the device can be manually forced to operate in the battery-backup mode by connecting MSWITCH to V_{DD}. The table below shows the different switchover modes.

	MSWITCH	STATUS
V_{DD} mode	GND	V_{DD} mode
	V_{DD}	Switch to battery-backup mode
Battery-backup mode	GND	Battery-backup mode
	V_{DD}	Battery-backup mode

If the manual switchover feature is not used, MSWITCH must be connected to ground.

watchdog

In a microprocessor- or DSP-based system, it is not only important to supervise the supply voltage, it is also important to ensure the correct program execution. The task of a watchdog is to ensure that the program is not stalled in an indefinite loop. The microprocessor, microcontroller, or the DSP have to toggle the watchdog input within typically 0.8 s to avoid a time-out from occurring. Either a low-to-high or a high-to-low transition resets the internal watchdog timer. If the input is unconnected the watchdog is disabled and will be retriggered internally.

saving current while using the watchdog

The watchdog input is internally driven low during the first 7/8 of the watchdog time-out period, then momentarily pulses high, resetting the watchdog counter. For minimum watchdog input current (minimum overall power consumption), leave WDI low for the majority of the watchdog time-out period, pulsing it low-high-low once within 7/8 of the watchdog time-out period to reset the watchdog timer. If instead, WDI is externally driven high for the majority of the time-out period, a current of e.g. 5 V/40 kΩ ≈ 125 μA can flow into WDI.




Figure 4. Watchdog Timing

absolute maximum ratings over operating free-air temperature (unless otherwise noted)†

Supply voltage: V_{DD} (see Note1) . . . . . 7 V
$\overline{MR}$ and WDI . . . . . −0.3 V to (V_{DD} + 0.3 V)
All other pins (see Note 1) . . . . . −0.3 V to 7 V
Continuous output current at V_{OUT}: I_O . . . . . 300 mA
All other pins, I_O . . . . . ±10 mA
Continuous total power dissipation . . . . . See Dissipation Rating Table
Operating free-air temperature range, T_A . . . . . −40°C to 85°C
Storage temperature range, T_{stg} . . . . . −65°C to 150°C
Lead temperature soldering 1,6 mm (1/16 inch) from case for 10 seconds . . . . . 260°C

† Stresses beyond those listed under “absolute maximum ratings” may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under “recommended operating conditions” is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

NOTE 1: All voltage values are with respect to GND. For reliable operation the device must not be operated at 7 V for more than t = 1000h continuously.

DISSIPATION RATING TABLE

PACKAGE	T_A < 25°C POWER RATING	DERATING FACTOR ABOVE T_A = 25°C	T_A = 70°C POWER RATING	T_A = 85°C POWER RATING
PW	700 mW	5.6 mW/°C	448 mW	364 mW

recommended operating conditions at specified temperature range

	MIN	MAX	UNIT
Supply voltage, V_{DD}	1.65	5.5	V
Battery supply voltage, V_{BAT}	1.5	5.5	V
Input voltage, V_I	0	V_{OUT} + 0.3	V
High-level input voltage, V_{IH}	0.7 x V_{OUT}		V
Low-level input voltage, all other pins, V_{IL}		0.3 x V_{OUT}	V
Continuous output current at V_{OUT}, I_O		200	mA
Input transition rise and fall rate at WDI, MSWITCH, $\Delta t/\Delta V$		100	ns/V
Slew rate at V_{DD} or V_{BAT}		34	mV/µs
Operating free-air temperature range, T_A	−40	85	°C

electrical characteristics over recommended operating conditions (unless otherwise noted)

PARAMETER			TEST CONDITIONS	MIN	TYP	MAX	UNIT
V_{OH}	High-level output voltage	$\overline{\text{RESET}}$, BATTOK, BATTON	V_{OUT} = 2.0 V, I_{OH} = −400 µA	V_{OUT} − 0.2 V			V
			V_{OUT} = 3.3 V, I_{OH} = −2 mA	V_{OUT} − 0.4 V			
			V_{OUT} = 5.0 V, I_{OH} = −3 mA				
		$\overline{\text{PFO}}$	V_{OUT} = 1.8 V, I_{OH} = −20 µA	V_{OUT} − 0.3 V			
			V_{OUT} = 3.3 V, I_{OH} = −80 µA	V_{OUT} − 0.4 V			
			V_{OUT} = 5.0 V, I_{OH} = −120 µA				
		$\overline{\text{CEOUT}}$ Enable mode $\overline{\text{CEIN}}$ = V_{OUT}	V_{OUT} = 2.0 V, I_{OH} = −1 mA	V_{OUT} − 0.2 V			
			V_{OUT} = 3.3 V, I_{OH} = −2 mA	V_{OUT} − 0.3 V			
			V_{OUT} = 5.0 V, I_{OH} = −5 mA				
		$\overline{\text{CEOUT}}$ Disable mode	V_{OUT} = 3.3 V, I_{OH} = −0.5 mA	V_{OUT} − 0.4 V			
V_{OL}	Low-level output voltage	$\overline{\text{RESET}}$, $\overline{\text{PFO}}$, BATTOK	V_{OUT} = 2.0 V, I_{OL} = 400 µA			0.2	V
			V_{OUT} = 3.3 V, I_{OL} = 2 mA			0.4	
			V_{OUT} = 5.0 V, I_{OL} = 3 mA				
		BATTON	V_{OUT} = 1.8 V, I_{OL} = 500 µA			0.2	
			V_{OUT} = 3.3 V, I_{OL} = 3 mA			0.4	
			V_{OUT} = 5.0 V, I_{OL} = 5 mA				
		$\overline{\text{CEOUT}}$ Enable mode $\overline{\text{CEIN}}$ = 0 V	V_{OUT} = 2.0 V, I_{OL} = 1 mA			0.2	
			V_{OUT} = 3.3 V, I_{OL} = 2 mA			0.3	
			V_{OUT} = 5.0 V, I_{OL} = 5 mA				
V_{res}	Power-up reset voltage (see Note 2)		V_{BAT} > 1.1 V OR V_{DD} > 1.4 V, I_{OL} = 20 µA			0.4	V
V_{OUT}	Normal mode		I_O = 5 mA, V_{DD} = 1.8 V	V_{DD} − 50 mV			V
			I_O = 75 mA, V_{DD} = 3.3 V	V_{DD} − 150 mV			
			I_O = 150 mA, V_{DD} = 5 V	V_{DD} − 250 mV			
	Battery-backup mode		I_O = 4 mA, V_{BAT} = 1.5 V	V_{BAT} − 50 mV			
			I_O = 75 mA, V_{BAT} = 3.3 V	V_{BAT} − 150 mV			
$r_{ds(on)}$	V_{DD} to V_{OUT} on-resistance		V_{DD} = 3.3 V		1	2	Ω
	V_{BAT} to V_{OUT} on-resistance		V_{BAT} = 3.3 V		1	2	
V_{IT}	Negative-going input threshold voltage (see Notes 3 and 4)	TPS3600x20	T_A = −40°C to 85°C	1.74	1.78	1.82	V
		TPS3600x25		2.17	2.22	2.27	
		TPS3600x30		2.57	2.63	2.69	
		TPS3600x33		2.87	2.93	2.99	
		TPS3600x50		4.31	4.40	4.49	
$V_{(PFI)}$		PFI		1.13	1.15	1.17	
$V_{(BOK)}$		TPS3600Dxx		V_{IT} + 5.8%	V_{IT} + 7.1%	V_{IT} + 8.3%	
$V_{(SWN)}$	Battery switch threshold voltage negative-going V_{OUT}			V_{IT} + 1%	V_{IT} + 2%	V_{IT} + 3.2%	V

NOTES: 2. The lowest supply voltage at which $\overline{\text{RESET}}$ becomes active. $t_{r(VDD)} \geq 15$ µs/V.
3. To ensure best stability of the threshold voltage, a bypass capacitor (ceramic, 0.1 µF) should be placed near the supply terminal.
4. Voltage is sensed at V_{OUT}

electrical characteristics over recommended operating conditions (unless otherwise noted) (continued)

PARAMETER			TEST CONDITIONS	MIN	TYP	MAX	UNIT
V_{hys}	Hysteresis	V_{IT}	$1.65\ V < V_{IT} < 2.5\ V$		20		mV
			$2.5\ V < V_{IT} < 3.5\ V$		40		
			$3.5\ V < V_{IT} < 5.5\ V$		50		
		BATTOK	$1.65\ V < V_{(BOK)} < 2.5\ V$		30		
			$2.5\ V < V_{(BOK)} < 3.5\ V$		60		
			$3.5\ V < V_{(BOK)} < 5.5\ V$		100		
		PFI			12		
		$V_{(BSW)}$	$V_{DD} = 1.8\ V$		66		
		$V_{(SWN)}$	$1.65\ V < V_{(SWN)} < 2.5\ V$		85		
			$2.5\ V < V_{(SWN)} < 3.5\ V$		100		
			$3.5\ V < V_{(SWN)} < 5.5\ V$		110		
I_{IH}	High-level input current	WDI (see Note 5)	$\overline{WDI} = V_{DD} = 5\ V$			150	µA
		$\overline{MR}$	$\overline{MR} = 0.7 \times V_{DD}$, $V_{DD} = 5\ V$	−33		−76	
I_{IL}	Low-level input current	WDI (see Note 5)	WDI = 0 V, $V_{DD} = 5\ V$			−150	
		$\overline{MR}$	$\overline{MR}$ = 0 V, $V_{DD} = 5\ V$	−110		−255	
I_I	Input current	PFI, MSWITCH	$V_I < V_{DD}$	−25		25	nA
I_{OS}	Short-circuit current	$\overline{PFO}$	$\overline{PFO}$ = 0 V, $V_{DD} = 1.8\ V$			−0.3	mA
			$\overline{PFO}$ = 0 V, $V_{DD} = 3.3\ V$			−1.1	
			$\overline{PFO}$ = 0 V, $V_{DD} = 5\ V$			−2.4	
I_{DD}	V_{DD} supply current		$V_{OUT} = V_{DD}$			40	µA
			$V_{OUT} = V_{BAT}$			8	
$I_{(BAT)}$	V_{BAT} supply current		$V_{OUT} = V_{DD}$	−0.1		0.1	µA
			$V_{OUT} = V_{BAT}$			40	
I_{lkg}	$\overline{CEIN}$ leakage current		Disable mode, $V_I < V_{DD}$			±1	µA
C_i	Input capacitance		V_I = 0 V to 5.0 V		5		pF

NOTE 5: For details on how to optimize current consumption when using WDI, see the detailed description section.

timing requirements at R_L = 1 MΩ, C_L = 50 pF, T_A = −40°C to 85°C

PARAMETER			TEST CONDITIONS	MIN	TYP	MAX	UNIT
t_w	Pulse width	V_{DD}	$V_{IH} = V_{IT} + 0.2$ V, $V_{IL} = V_{IT} - 0.2$ V	5	1		µs
		$\overline{MR}$	$V_{DD} > V_{IT} + 0.2$ V, $V_{IL} = 0.3 \times V_{DD}$, $V_{IH} = 0.7 \times V_{DD}$	100			ns
		WDI					

switching characteristics at R_L= 1 MΩ, C_L = 50 pF, T_A = −40°C to 85°C

PARAMETER			TEST CONDITIONS	MIN	TYP	MAX	UNIT
t_d	Delay time		$V_{DD} \geq V_{IT} + 0.2$ V, $\overline{MR} \geq 0.7 \times V_{DD}$, See timing diagram	60	100	140	ms
$t_{(tout)}$	Watchdog time-out		$V_{DD} > V_{IT} + 0.2$ V, See timing diagram	0.48	0.8	1.12	s
t_{PLH}	Propagation (delay) time, low-to-high-level output	50% $\overline{RESET}$ to 50% $\overline{CEOUT}$	$V_{OUT} = V_{IT}$		15		µs
t_{PHL}	Propagation (delay) time, high-to-low-level output	V_{DD} to $\overline{RESET}$	$V_{IL} = V_{IT} - 0.2$ V, $V_{IH} = V_{IT} + 0.2$ V		2	5	µs
		PFI to $\overline{PFO}$	$V_{IL} = V_{(PFI)} - 0.2$ V, $V_{IH} = V_{(PFI)} + 0.2$ V		3	5	µs
		$\overline{MR}$ to $\overline{RESET}$	$V_{DD} \geq V_{IT} + 0.2$ V, $V_{IL} = 0.3 \times V_{DD}$, $V_{IH} = 0.7 \times V_{DD}$		0.1	1	µs
		50% $\overline{CEIN}$ to 50% $\overline{CEOUT}$ CL = 50 pF only (see Note 6)	V_{DD} = 1.8 V		5	15	ns
			V_{DD} = 3.3 V		1.6	5	ns
			V_{DD} = 5 V		1	3	ns
	Transition time	V_{DD} to BATTON	$V_{IL} = V_{BAT} - 0.2$ V, $V_{IH} = V_{BAT} + 0.2$ V, $V_{(BAT)} < V_{IT}$			3	µs

NOTE 6: Ensured by design.

TYPICAL CHARACTERISTICS

Table of Graphs

			FIGURE
$r_{DS(on)}$	Static Drain-source on-state resistance V_{DD} to V_{OUT}	vs Output current	5
	Static Drain-source on-state resistance V_{BAT} to V_{OUT}		6
	Static Drain-source on-state resistance	vs Chip enable input voltage	7
I_{DD}	Supply current	vs Supply voltage	8, 9
V_{IT}	Normalized threshold voltage	vs Free-air temperature	10
V_{OH}	High-level output voltage at $\overline{RESET}$	vs High-level output current	11, 12
	High-level output voltage at $\overline{PFO}$		13, 14
	High-level output voltage at $\overline{CEOUT}$		15, 16, 17, 18
V_{OL}	Low-level output voltage at $\overline{RESET}$	vs Low-level output current	19, 20
	Low-level output voltage at $\overline{CEOUT}$		21, 22
	Low-level output voltage at BATTON		23, 24
$t_{p(min)}$	Minimum Pulse Duration at V_{DD}	vs Threshold voltage overdrive at V_{DD}	25
	Minimum Pulse Duration at PFI	vs Threshold voltage overdrive at PFI	26

TYPICAL CHARACTERISTICS

**STATIC DRAIN SOURCE ON-STATE RESISTANCE
(V_{DD} TO V_{OUT})
vs
OUTPUT CURRENT**




Figure 5

**STATIC DRAIN SOURCE ON-STATE RESISTANCE
(V_{BAT} TO V_{OUT})
vs
OUTPUT CURRENT**




Figure 6

**STATIC DRAIN SOURCE ON-STATE RESISTANCE
(CEIN to CEOUT)
vs
CHIP-ENABLE INPUT VOLTAGE**




Figure 7

**SUPPLY CURRENT
vs
SUPPLY VOLTAGE**




Figure 8

TYPICAL CHARACTERISTICS

SUPPLY CURRENT vs SUPPLY VOLTAGE




Figure 9

NORMALIZED THRESHOLD VOLTAGE vs FREE-AIR TEMPERATURE




Figure 10

HIGH-LEVEL OUTPUT VOLTAGE AT $\overline{\text{RESET}}$ vs HIGH-LEVEL OUTPUT CURRENT




Figure 11

HIGH-LEVEL OUTPUT VOLTAGE AT $\overline{\text{RESET}}$ vs HIGH-LEVEL OUTPUT CURRENT




Figure 12

TYPICAL CHARACTERISTICS

HIGH-LEVEL OUTPUT VOLTAGE AT $\overline{PFO}$
vs
HIGH-LEVEL OUTPUT CURRENT




Figure 13

HIGH-LEVEL OUTPUT VOLTAGE AT $\overline{PFO}$
vs
HIGH-LEVEL OUTPUT CURRENT




Figure 14

HIGH-LEVEL OUTPUT VOLTAGE AT $\overline{CEOUT}$
vs
HIGH-LEVEL OUTPUT CURRENT




Figure 15

HIGH-LEVEL OUTPUT VOLTAGE AT $\overline{CEOUT}$
vs
HIGH-LEVEL OUTPUT CURRENT




Figure 16

TYPICAL CHARACTERISTICS

HIGH-LEVEL OUTPUT VOLTAGE AT $\overline{\text{CEOUT}}$ vs HIGH-LEVEL OUTPUT CURRENT




Figure 17

HIGH-LEVEL OUTPUT VOLTAGE AT $\overline{\text{CEOUT}}$ vs HIGH-LEVEL OUTPUT CURRENT




Figure 18

LOW-LEVEL OUTPUT VOLTAGE AT $\overline{\text{RESET}}$ vs LOW-LEVEL OUTPUT CURRENT




Figure 19

LOW-LEVEL OUTPUT VOLTAGE AT $\overline{\text{RESET}}$ vs LOW-LEVEL OUTPUT CURRENT




Figure 20

TYPICAL CHARACTERISTICS

LOW-LEVEL OUTPUT VOLTAGE AT $\overline{\text{CEOUT}}$
vs
LOW-LEVEL OUTPUT CURRENT




Figure 21

LOW-LEVEL OUTPUT VOLTAGE AT $\overline{\text{CEOUT}}$
vs
LOW-LEVEL OUTPUT CURRENT




Figure 22

LOW-LEVEL OUTPUT VOLTAGE AT BATTON
vs
LOW-LEVEL OUTPUT CURRENT




Figure 23

LOW-LEVEL OUTPUT VOLTAGE AT BATTON
vs
LOW-LEVEL OUTPUT CURRENT




Figure 24

TYPICAL CHARACTERISTICS

TPS3600D50
MINIMUM PULSE DURATION AT V_{DD}
vs
THRESHOLD OVERDRIVE AT V_{DD}




Figure 25

TPS3600D50
MINIMUM PULSE DURATION AT PFI
vs
THRESHOLD OVERDRIVE AT PFI




Figure 26

PACKAGING INFORMATION

Orderable Device	Status [1]	Package Type	Package Drawing	Pins	Package Qty	Eco Plan [2]	Lead/Ball Finish	MSL Peak Temp [3]
TPS3600D20PW	ACTIVE	TSSOP	PW	14	90	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TPS3600D20PWG4	ACTIVE	TSSOP	PW	14	90	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TPS3600D20PWR	ACTIVE	TSSOP	PW	14	2000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TPS3600D20PWRG4	ACTIVE	TSSOP	PW	14	2000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TPS3600D25PW	ACTIVE	TSSOP	PW	14	90	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TPS3600D25PWG4	ACTIVE	TSSOP	PW	14	90	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TPS3600D25PWR	ACTIVE	TSSOP	PW	14	2000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TPS3600D25PWRG4	ACTIVE	TSSOP	PW	14	2000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TPS3600D33PW	ACTIVE	TSSOP	PW	14	90	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TPS3600D33PWG4	ACTIVE	TSSOP	PW	14	90	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TPS3600D33PWR	ACTIVE	TSSOP	PW	14	2000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TPS3600D33PWRG4	ACTIVE	TSSOP	PW	14	2000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TPS3600D50PW	ACTIVE	TSSOP	PW	14	90	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TPS3600D50PWG4	ACTIVE	TSSOP	PW	14	90	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TPS3600D50PWR	ACTIVE	TSSOP	PW	14		TBD	Call TI	Call TI
TPS3600D50PWRG4	ACTIVE	TSSOP	PW	14		TBD	Call TI	Call TI

[1] The marketing status values are defined as follows:
ACTIVE: Product device recommended for new designs.
LIFEBUY: TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.
NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.
PREVIEW: Device has been announced but is not in production. Samples may or may not be available.
OBSOLETE: TI has discontinued the production of the device.


[2] Eco Plan - The planned eco-friendly classification: Pb-Free (RoHS), Pb-Free (RoHS Exempt), or Green (RoHS & no Sb/Br) - please check http://www.ti.com/productcontent for the latest availability information and additional product content details.
TBD: The Pb-Free/Green conversion plan has not been defined.
Pb-Free (RoHS): TI's terms "Lead-Free" or "Pb-Free" mean semiconductor products that are compatible with the current RoHS requirements for all 6 substances, including the requirement that lead not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, TI Pb-Free products are suitable for use in specified lead-free processes.
Pb-Free (RoHS Exempt): This component has a RoHS exemption for either 1) lead-based flip-chip solder bumps used between the die and package, or 2) lead-based die adhesive used between the die and leadframe. The component is otherwise considered Pb-Free (RoHS compatible) as defined above.
Green (RoHS & no Sb/Br): TI defines "Green" to mean Pb-Free (RoHS compatible), and free of Bromine (Br) and Antimony (Sb) based flame retardants (Br or Sb do not exceed 0.1% by weight in homogeneous material)

[3] MSL, Peak Temp. -- The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

TAPE AND REEL INFORMATION




A0	Dimension designed to accommodate the component width
B0	Dimension designed to accommodate the component length
K0	Dimension designed to accommodate the component thickness
W	Overall width of the carrier tape
P1	Pitch between successive cavity centers

*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
TPS3600D20PWR	TSSOP	PW	14	2000	330.0	12.4	7.0	5.6	1.6	8.0	12.0	Q1
TPS3600D25PWR	TSSOP	PW	14	2000	330.0	12.4	7.0	5.6	1.6	8.0	12.0	Q1
TPS3600D33PWR	TSSOP	PW	14	2000	330.0	12.4	7.0	5.6	1.6	8.0	12.0	Q1

TAPE AND REEL BOX DIMENSIONS




*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
TPS3600D20PWR	TSSOP	PW	14	2000	340.5	338.1	20.6
TPS3600D25PWR	TSSOP	PW	14	2000	340.5	338.1	20.6
TPS3600D33PWR	TSSOP	PW	14	2000	340.5	338.1	20.6

PW (R-PDSO-G)** **PLASTIC SMALL-OUTLINE PACKAGE**

14 PINS SHOWN



DIM \ PINS **	8	14	16	20	24	28
A MAX	3,10	5,10	5,10	6,60	7,90	9,80
A MIN	2,90	4,90	4,90	6,40	7,70	9,60

4040064/F 01/97

NOTES: A. All linear dimensions are in millimeters.
B. This drawing is subject to change without notice.
C. Body dimensions do not include mold flash or protrusion not to exceed 0,15.
D. Falls within JEDEC MO-153

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products		**Applications**	
Amplifiers	amplifier.ti.com	Audio	www.ti.com/audio
Data Converters	dataconverter.ti.com	Automotive	www.ti.com/automotive
DLP® Products	www.dlp.com	Broadband	www.ti.com/broadband
DSP	dsp.ti.com	Digital Control	www.ti.com/digitalcontrol
Clocks and Timers	www.ti.com/clocks	Medical	www.ti.com/medical
Interface	interface.ti.com	Military	www.ti.com/military
Logic	logic.ti.com	Optical Networking	www.ti.com/opticalnetwork
Power Mgmt	power.ti.com	Security	www.ti.com/security
Microcontrollers	microcontroller.ti.com	Telephony	www.ti.com/telephony
RFID	www.ti-rfid.com	Video & Imaging	www.ti.com/video
RF/IF and ZigBee® Solutions	www.ti.com/lprf	Wireless	www.ti.com/wireless

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2009, Texas Instruments Incorporated