


## SLLIMM high power IPM, 3-phase inverter, 50 A, 650 V short-circuit rugged IGBT



### Product status link

[STGIK50CH65T](#)

### Product summary

|            |              |
|------------|--------------|
| Order code | STGIK50CH65T |
| Marking    | GIK50CH65T   |
| Package    | SDIPHP-30L   |
| Packing    | Tube         |

### Features

- IPM 650 V, 50 A 3-phase inverter bridge including control ICs for gates driving
- 3.3 V, 5 V TTL/CMOS inputs with hysteresis
- Undervoltage lockout of gate drivers
- Built-in bootstrap diodes
- Short-circuit protection
- Shutdown input/fault output
- Separate open emitter outputs
- Comparator for fault protection
- Short-circuit rugged
- Very fast, soft recovery diodes
- Fully isolated package
- Isolation rating of 2500 Vrms/min
- 100 kΩ NTC for temperature monitoring
- UL recognition: UL 1557, file E81734

### Application


- HVAC
- GPI
- Servo motor
- Pumps and compressors

### Description

This new IPM (intelligent power module) is part of the high power SLLIMM (small low-loss intelligent molded module) family and provides a compact, high-performance AC motor drive in a simple, rugged design. It combines driver control with improved short-circuit rugged 650 V trench gate field-stop IGBTs, resulting ideal for 3-phase inverters motor drives.

## 1 Internal schematic and pin description

**Figure 1. Internal schematic diagram and pin configuration**



GADG170920211009GT

**Table 1. Pin description**

| Pin | Symbol | Description                                |
|-----|--------|--------------------------------------------|
| 1   | OUTu   | High-side reference output for U phase     |
| 2   | VBOOTu | Bootstrap voltage for U phase              |
| 3   | VCCHu  | High-side voltage power supply for U phase |
| 4   | HINu   | High-side logic input for U phase          |
| 5   | OUTv   | High-side reference output for V phase     |
| 6   | VBOOTv | Bootstrap voltage for V phase              |
| 7   | VCCHv  | High-side voltage power supply for V phase |
| 8   | HINv   | High-side logic input for V phase          |
| 9   | OUTw   | High-side reference output for W phase     |
| 10  | VBOOTw | Bootstrap voltage for W phase              |
| 11  | VCCHw  | High-side voltage power supply for W phase |
| 12  | HINw   | High-side logic input for W phase          |
| 13  | NC     | Not connected (cut pin)                    |
| 14  | T      | NTC thermistor output                      |
| 15  | LINu   | Low-side logic input for U phase           |
| 16  | LINv   | Low-side logic input for V phase           |
| 17  | LINw   | Low-side logic input for W phase           |
| 18  | FO     | Shutdown/fault output                      |
| 19  | CFO    | Capacitor for fault output setting         |
| 20  | CIN    | Comparator input                           |
| 21  | GND    | Ground                                     |
| 22  | VCCL   | Low-side voltage power supply              |
| 23  | NW     | Negative DC input for W phase              |
| 24  | NV     | Negative DC input for V phase              |
| 25  | NU     | Negative DC input for U phase              |
| 26  | W      | W phase output                             |
| 27  | V      | V phase output                             |
| 28  | U      | U phase output                             |
| 29  | P      | Positive DC input                          |
| 30  | NC     | Not connected                              |

**Note:** *It is required the external connection between the following couple of pins:*

- OUTu (1) and U (28)
- OUTv (5) and V (27)
- OUTw (9) and W (26).

## 2 Absolute maximum ratings

$T_J = 25\text{ °C}$  unless otherwise noted.

**Table 2. Inverter parts**

| Symbol          | Parameter                                                                                                                                 | Value | Unit |
|-----------------|-------------------------------------------------------------------------------------------------------------------------------------------|-------|------|
| $V_{PN}$        | Supply voltage between P - $N_U$ , - $N_V$ , - $N_W$                                                                                      | 500   | V    |
| $V_{PN(surge)}$ | Supply voltage (surge) between P - $N_U$ , - $N_V$ , - $N_W$                                                                              | 550   | V    |
| $V_{CES}$       | Collector-emitter voltage each IGBT                                                                                                       | 650   | V    |
| $I_C$           | Continuous collector current each IGBT                                                                                                    | 50    | A    |
| $I_{CP}$        | Peak collector current each IGBT (less than 1 ms)                                                                                         | 100   | A    |
| $P_{TOT}$       | Total power dissipation at $T_C = 25\text{ °C}$ each IGBT                                                                                 | 150   | W    |
| $V_{PN(SP)}$    | Self-protection supply voltage limit, $V_{CC} = 13.5 - 16.5\text{ V}$ , $T_J = 150\text{ °C}$ , non-repetitive, less than 2 $\mu\text{s}$ | 400   | V    |

**Table 3. Control parts**

| Symbol                   | Parameter                                                      | Min.  | Max.           | Unit             |
|--------------------------|----------------------------------------------------------------|-------|----------------|------------------|
| $V_{CC}$                 | Supply voltage applied between $V_{CCHx}$ -GND, $V_{CCL}$ -GND | - 0.5 | 25             | V                |
| $V_{BOOT}$               | Bootstrap voltage                                              | - 0.5 | 25             | V                |
| $V_{OUT}$                | Output voltage applied between $OUTx$ and GND                  | - 0.5 | 650            | V                |
| $V_{CIN}$                | Comparator input voltage                                       | - 0.5 | $V_{CCL}+0.3$  | V                |
| $V_{INH}$                | Logic input voltage applied between $H_{INx}$ and GND          | - 0.5 | $V_{CCHx}+0.3$ | V                |
| $V_{INL}$                | Logic input voltage applied between $L_{INx}$ and GND          | - 0.5 | $V_{CCL}+0.3$  | V                |
| $V_{FO}$                 | Fault output voltage                                           | - 0.5 | $V_{CCL}+0.3$  | V                |
| $I_{FO}$                 | Fault output sink current                                      |       | 1              | mA               |
| $\Delta V_{CC}/\Delta t$ | Change rate of $V_{CC}$ supply voltage time                    | -1    | 1              | V/ $\mu\text{s}$ |

**Table 4. Bootstrap diode**

| Symbol     | Parameter                       | Min. | Max. | Unit |
|------------|---------------------------------|------|------|------|
| $V_{R-BS}$ | Bootstrap diode reverse voltage | -    | 650  | V    |

**Table 5. Total system**

| Symbol    | Parameter                                                                                                 | Value      | Unit               |
|-----------|-----------------------------------------------------------------------------------------------------------|------------|--------------------|
| $V_{ISO}$ | Isolation withstand voltage applied between each pin and heat sink plate (AC voltage, $t = 60\text{ s}$ ) | 2500       | Vrms               |
| $T_J$     | IGBT and FRD operating junction temperature range                                                         | -40 to 175 | $^{\circ}\text{C}$ |
|           | Driver IC and bootstrap diode operating junction temperature range                                        | -40 to 150 |                    |
| $T_C$     | Module case operating temperature range                                                                   | -40 to 125 | $^{\circ}\text{C}$ |

**Table 6. Thermal data**

| Symbol     | Parameter                                         | Value | Unit |
|------------|---------------------------------------------------|-------|------|
| $R_{thJC}$ | Thermal resistance, junction-to-case single IGBT  | 1     | °C/W |
|            | Thermal resistance, junction-to-case single diode | 2     |      |

### 3 Electrical characteristics

$T_J = 25\text{ }^{\circ}\text{C}$  unless otherwise specified.

#### 3.1 Inverter parts

**Table 7. Inverter parts**

| Symbol        | Parameter                            | Test conditions                                                                                                                | Min. | Typ. | Max. | Unit          |
|---------------|--------------------------------------|--------------------------------------------------------------------------------------------------------------------------------|------|------|------|---------------|
| $I_{CES}$     | Collector cut-off current            | $V_{CE} = 650\text{ V}$ , $V_{CC} = V_{boot} = 15\text{ V}$                                                                    | -    | 25   |      | $\mu\text{A}$ |
| $V_{CE(sat)}$ | Collector-emitter saturation voltage | $V_{CC} = V_{boot} = 15\text{ V}$ , $V_{IN}^{(1)} = 5\text{ V}$ ,<br>$I_C = 50\text{ A}$                                       | -    | 1.8  | 2.3  | V             |
|               |                                      | $V_{CC} = V_{boot} = 15\text{ V}$ , $V_{IN}^{(1)} = 5\text{ V}$ ,<br>$I_C = 50\text{ A}$ , $T_J = 175\text{ }^{\circ}\text{C}$ | -    | 2.2  |      |               |
| $V_F$         | Diode forward voltage                | $V_{IN}^{(1)} = 0\text{ V}$ , $I_C = 50\text{ A}$                                                                              | -    | 2.0  | 2.5  | V             |
|               |                                      | $V_{IN}^{(1)} = 0\text{ V}$ , $I_C = 50\text{ A}$ , $T_J = 175\text{ }^{\circ}\text{C}$                                        | -    | 2.25 |      |               |

1. Applied between  $HINx$ ,  $LINx$  and  $GND$  for  $x = U, V, W$ .

**Table 8. Inductive load switching time and energy**

| Symbol                             | Parameter                 | Test conditions                                                                                                                          | Min. | Typ.  | Max. | Unit |
|------------------------------------|---------------------------|------------------------------------------------------------------------------------------------------------------------------------------|------|-------|------|------|
| High-side                          |                           |                                                                                                                                          |      |       |      |      |
| t <sub>on</sub> <sup>(1)</sup>     | Turn-on time              | V <sub>DD</sub> = 300 V, V <sub>CC</sub> = V <sub>boot</sub> = 15 V,<br>V <sub>IN</sub> <sup>(2)</sup> = 0 to 5 V, I <sub>C</sub> = 50 A | -    | 860   | -    | ns   |
| t <sub>c(on)</sub> <sup>(1)</sup>  | Crossover time on         |                                                                                                                                          | -    | 386   | -    | ns   |
| t <sub>off</sub> <sup>(1)</sup>    | Turn-off time             |                                                                                                                                          | -    | 1464  | -    | ns   |
| t <sub>c(off)</sub> <sup>(1)</sup> | Crossover time off        |                                                                                                                                          | -    | 137   | -    | ns   |
| t <sub>rr</sub> <sup>(1)</sup>     | Reverse recovery time     |                                                                                                                                          | -    | 370   | -    | ns   |
| E <sub>on</sub>                    | Turn-on switching energy  |                                                                                                                                          | -    | 2.70  | -    | mJ   |
| E <sub>off</sub>                   | Turn-off switching energy |                                                                                                                                          | -    | 1.12  | -    | mJ   |
| E <sub>rr</sub>                    | Reverse recovery energy   |                                                                                                                                          | -    | 0.244 | -    | mJ   |
| Low-side                           |                           |                                                                                                                                          |      |       |      |      |
| t <sub>on</sub> <sup>(1)</sup>     | Turn-on time              | V <sub>DD</sub> = 300 V, V <sub>CC</sub> = V <sub>boot</sub> = 15 V,<br>V <sub>IN</sub> <sup>(2)</sup> = 0 to 5 V, I <sub>C</sub> = 50 A | -    | 605   | -    | ns   |
| t <sub>c(on)</sub> <sup>(1)</sup>  | Crossover time on         |                                                                                                                                          | -    | 266   | -    | ns   |
| t <sub>off</sub> <sup>(1)</sup>    | Turn-off time             |                                                                                                                                          | -    | 962   | -    | ns   |
| t <sub>c(off)</sub> <sup>(1)</sup> | Crossover time off        |                                                                                                                                          | -    | 110   | -    | ns   |
| t <sub>rr</sub> <sup>(1)</sup>     | Reverse recovery time     |                                                                                                                                          | -    | 405   | -    | ns   |
| E <sub>on</sub>                    | Turn-on switching energy  |                                                                                                                                          | -    | 2.16  | -    | mJ   |
| E <sub>off</sub>                   | Turn-off switching energy |                                                                                                                                          | -    | 0.85  | -    | mJ   |
| E <sub>rr</sub>                    | Reverse recovery energy   |                                                                                                                                          | -    | 0.192 | -    | mJ   |

1.  $t_{on}$  and  $t_{off}$  include the propagation delay time of the internal drive.  $t_{c(on)}$  and  $t_{c(off)}$  are the switching times of the IGBT itself under the internally given gate driving conditions.

2. Applied between  $HINx$ ,  $LINx$  and  $GND$  for  $x = U, V, W$ .

### Figure 3. Switching time definition



## 3.2 Control/protection parts

Unless specifically noted,  $T_C = -40\text{ }^{\circ}\text{C}$  to  $125\text{ }^{\circ}\text{C}$ ,  $V_{PN} = 300\text{ V}$ ,  $V_{VCCxH} = V_{VCCL} = 15\text{ V}$ ,  $R_{FF} = 10\text{ k}\Omega$ ,  $C_{FF} = 0\text{ }\mu\text{F}$ , and  $V_{FO} = 5\text{ V}$ . The shipping test is performed at  $T_A = 25\text{ }^{\circ}\text{C}$  and  $125\text{ }^{\circ}\text{C}$  for the electrical characteristics shown below (except for the parameters specified by design and not tested in production).

**Table 9. Control/protection parts**

| Symbol                                    | Parameter                                   | Test condition                                                                       | Min. | Typ. | Max. | Unit |
|-------------------------------------------|---------------------------------------------|--------------------------------------------------------------------------------------|------|------|------|------|
| V <sub>VCCHx_H</sub>                      | VCCHx pin operating voltage                 |                                                                                      | 9.2  | 10.2 | 11.3 | V    |
| V <sub>VCCHx_L</sub>                      | VCCHx pin operating stop voltage            |                                                                                      | 8.7  | 9.7  | 10.8 | V    |
| V <sub>VCCHx_HYS</sub>                    | VCCHx pin hysteresis                        |                                                                                      |      | 0.5  |      | V    |
| V <sub>VCCL_H</sub>                       | VCCL pin operating voltage                  |                                                                                      | 11.2 | 12.6 | 13.3 | V    |
| V <sub>VCCL_L</sub>                       | VCCL pin operating stop voltage             |                                                                                      | 10.7 | 12.1 | 12.8 | V    |
| V <sub>VCCL_HYS</sub>                     | VCCL pin hysteresis                         |                                                                                      |      | 0.5  |      | V    |
| V <sub>VBOOTx-OUTx_H</sub>                | VBOOTx-OUTx operating voltage               |                                                                                      | 11.0 | 12.1 | 12.8 | V    |
| V <sub>VBOOTx-OUTx_L</sub>                | VBOOTx-OUTx operating stop voltage          |                                                                                      | 10.5 | 11.6 | 12.3 | V    |
| V <sub>VBOOTx-OUTx_HYS</sub>              | VBOOTx-OUTx hysteresis                      |                                                                                      |      | 0.5  |      | V    |
| I <sub>VCCHx</sub>                        | VCCHx pin input current                     | V <sub>HINx</sub> = 0 V, each pin                                                    |      | 1.1  | 2.0  | mA   |
|                                           |                                             | V <sub>HINx</sub> = 5 V, each pin                                                    |      | 1.1  | 2.0  | mA   |
| I <sub>VCCL</sub>                         | VCCL pin input current                      | V <sub>LINx</sub> = 0 V                                                              |      | 1.9  | 3.2  | mA   |
|                                           |                                             | V <sub>LINx</sub> = 5 V                                                              |      | 1.9  | 3.2  | mA   |
| I <sub>VBOOTx-OUTx</sub>                  | VBOOTx-OUTx input current                   | V <sub>VBOOTx-OUTx</sub> = 15 V,<br>V <sub>INxH</sub> = 0 V,<br>in 1-phase operation |      | 0.09 | 0.30 | mA   |
|                                           |                                             | V <sub>VBOOTx-OUTx</sub> = 15 V,<br>V <sub>INxH</sub> = 5 V,<br>in 1-phase operation |      | 0.11 | 0.30 | mA   |
| Input signal                              |                                             |                                                                                      |      |      |      |      |
| V <sub>HINx_H</sub>                       | HINx pin high-level input threshold voltage |                                                                                      |      | 2.0  | 2.5  | V    |
| V <sub>HINx_L</sub>                       | HINx pin low-level input threshold voltage  |                                                                                      | 1.0  | 1.5  |      | V    |
| V <sub>HINx_HYS</sub>                     | HINx pin hysteresis                         |                                                                                      |      | 0.5  |      | V    |
| V <sub>LINx_H</sub>                       | LINx high-level input threshold voltage     |                                                                                      |      | 2.0  | 2.5  | V    |
| V <sub>LINx_L</sub>                       | LINx pin low-level input threshold voltage  |                                                                                      | 1.0  | 1.5  |      | V    |
| V <sub>LINx_HYS</sub>                     | LINx pin hysteresis                         |                                                                                      |      | 0.5  |      | V    |
| I <sub>HINx</sub>                         | HINx pin input Current                      | V <sub>HINx</sub> = 5 V, each pin                                                    |      | 0.25 | 0.50 | mA   |
| I <sub>LINx</sub>                         | LINx pin input Current                      | V <sub>LINx</sub> = 5 V, each pin                                                    |      | 0.25 | 0.50 | mA   |
| t <sub>HINx_MIN(ON)</sub> <sup>(1)</sup>  | HINx pin minimum response pulse width (On)  |                                                                                      |      | 0.34 | 0.50 | μs   |
| t <sub>HINx_MIN(OFF)</sub> <sup>(2)</sup> | HINx pin minimum response pulse width (Off) |                                                                                      |      | 0.36 | 0.50 | μs   |

| Symbol                                        | Parameter                                   | Test condition                                                                | Min.  | Typ.  | Max.  | Unit    |
|-----------------------------------------------|---------------------------------------------|-------------------------------------------------------------------------------|-------|-------|-------|---------|
| $t_{LINx\_MIN(ON)}^{(2)}$                     | LINx pin minimum response pulse width (On)  |                                                                               | -     | 0.26  | 0.50  | $\mu s$ |
| $t_{LINx\_MIN(OFF)}^{(2)}$                    | LINx pin minimum response pulse width (Off) |                                                                               | -     | 0.27  | 0.50  | $\mu s$ |
| Fault signal output and shutdown signal input |                                             |                                                                               |       |       |       |         |
| $V_{FO\_H}$                                   | FO pin shutdown release voltage             |                                                                               |       | 2.0   | 2.5   | V       |
| $V_{FO\_L}$                                   | FO pin shutdown threshold voltage           |                                                                               | 1.0   | 1.5   |       | V       |
| $V_{FO\_HYS}$                                 | FO pin shutdown hysteresis                  |                                                                               |       | 0.5   |       | V       |
| $V_{FO\_H}$                                   | FO pin output voltage in normal operation   | $V_{FO} = 5\text{ V}$ , $R_{FF} = 10\text{ k}\Omega$ , $V_{CIN} = 0\text{ V}$ | 4.8   | 5.0   |       | V       |
| $V_{FO\_L}$                                   | VFO pin error signal output voltage         | $V_{FO} = 5\text{ V}$ , $R_{FF} = 10\text{ k}\Omega$ , $V_{CIN} = 1\text{ V}$ | -     | 0.05  | 0.50  | V       |
| $t_{FO}^{(1)(2)}$                             | FO pin CIN hold time                        | $C_{CFO} = 0\text{ }\mu F$                                                    | 0.012 | 0.030 | 0.060 | ms      |
|                                               |                                             | $C_{CFO} = 0.001\text{ }\mu F$                                                | 0.20  | 0.32  | 0.44  | ms      |
|                                               |                                             | $C_{CFO} = 0.01\text{ }\mu F$                                                 | 2.0   | 3.2   | 4.4   | ms      |
|                                               |                                             | $C_{CFO} = 0.1\text{ }\mu F$                                                  | 20    | 32    | 44    | ms      |
|                                               |                                             | $C_{CFO} = 1\text{ }\mu F$                                                    | 200   | 320   | 440   | ms      |
| Protection                                    |                                             |                                                                               |       |       |       |         |
| $V_{CIN\_H}$                                  | CIN pin overcurrent detection voltage       |                                                                               | 0.46  | 0.50  | 0.54  | V       |
| $V_{CIN\_L}$                                  | CIN pin overcurrent release voltage         |                                                                               | 0.32  | 0.38  | 0.44  | V       |
| $V_{CIN\_HYS}$                                | CIN pin overcurrent hysteresis              |                                                                               |       | 0.12  |       | V       |
| $t_{CIN\_DELAY}$                              | CIN pin detection delay time                |                                                                               |       | 0.3   | 0.5   | $\mu s$ |
| $I_{CIN}$                                     | CIN pin input current                       | $V_{CIN} = 0.5\text{ V}$                                                      |       | 2.5   |       | $\mu A$ |

1. Specified by design, not tested in production.

2. For a relation between  $t_{FO}$  and  $C_{CFO}$ , see Figure 5. The shipping test is performed with the condition at  $C_{CFO} = 0.01\text{ }\mu F$  only.

**Figure 4. Total bootstrap current vs  $f_{sw}$**




**Figure 5.  $t_{FO}$  -  $C_{CFO}$  characteristics**





**Figure 6. CIN test circuit and time definition**



GADG200920211621GT

## 4 Bootstrap diode

**Table 10. Bootstrap diode**

| Symbol      | Parameter                       | Test conditions             | Min. | Typ. | Max. | Unit     |
|-------------|---------------------------------|-----------------------------|------|------|------|----------|
| $V_{F\_BS}$ | Bootstrap diode forward voltage | $I_{F\_BS} = 10 \text{ mA}$ | 0.4  | 0.9  | 1.4  | V        |
| $R_{S\_BS}$ | Bootstrap diode series resistor |                             | 12   | 20   | 28   | $\Omega$ |



**Figure 7. Bootstrap diode static characteristics**



## 5 NTC thermistor


**Table 11. NTC thermistor**

| Symbol      | Parameter                              | Test condition                     | Min. | Typ. | Max. | Unit               |
|-------------|----------------------------------------|------------------------------------|------|------|------|--------------------|
| $R_{25}$    | Resistance                             | $T_A = 25\text{ }^{\circ}\text{C}$ |      | 100  |      | k $\Omega$         |
| $B_{25/85}$ | B-constant (25–85 $^{\circ}\text{C}$ ) |                                    |      | 4395 |      | K                  |
| T           | Operating temperature range            |                                    | -40  |      | 175  | $^{\circ}\text{C}$ |

**Figure 8. NTC resistance vs temperature**

**Figure 9. NTC resistance vs temperature zoom**


## 6 Application circuit example

Figure 10. Application circuit example



Application designers are free to use a different scheme according to the device specifications.

## 6.1 Guidelines

1. External connections between the pins OUT<sub>U</sub>-U, OUT<sub>V</sub>-V and OUT<sub>W</sub>-w are required.
2. Input signals HIN, LIN are active-high logic. A 20 kΩ (typ.) pull-down resistor is built-in for each input pin. To prevent input signal oscillation, the wiring of each input should be as short as possible and the use of RC filters (R<sub>1</sub>, C<sub>1</sub>) on each input signal is suggested. The filters should be done with a time constant of about 100 ns and placed as close as possible to the IPM input pins.
3. The use of a bypass capacitor C<sub>VCC</sub> (aluminum or tantalum) can help reduce the transient circuit demand on the power supply. Also, to reduce high frequency switching noise distributed on the power lines, it is suggested to place a decoupling capacitor C<sub>3</sub> (100 to 220 nF, with low ESR and low ESL), as close as possible to each V<sub>CC</sub> pin and in parallel with the bypass capacitor.
4. The use of RC filter (R<sub>CF</sub>, C<sub>CF</sub>) for preventing protection circuit malfunction is suggested. The time constant (R<sub>CF</sub> × C<sub>CF</sub>) should be set to 1 μs and the filter must be placed as close as possible to the CIN pin.
5. The FO is an input/output pin. It should be pulled up to a power supply (i.e., MCU bias at 3.3 - 5 V) by a resistor value able to match the V<sub>FO\_L</sub> and V<sub>FO\_H</sub> threshold voltages mainly. In case of 3.3 or 5 V pull up voltage, the suggested resistor value is from 5.6 kΩ to 68 kΩ. The RC filter on FO could have also impact on the re-starting time after a fault event so it must be placed as close as possible to the FO pin.
6. A decoupling capacitor C<sub>2</sub> between 1 nF and 10 nF can be used to increase the noise immunity of the signal on the NTC thermistor. Its effectiveness is improved if the capacitor is placed close to the MCU.
7. The decoupling capacitor C<sub>4</sub> (100 to 220 nF with low ESR and low ESL) in parallel with each C<sub>BOOT</sub> is useful to filter high frequency disturbances. Both C<sub>BOOT</sub> and C<sub>4</sub> (if present) should be placed as close as possible to each OUT<sub>U</sub>, OUT<sub>V</sub>, OUT<sub>W</sub> and respective V<sub>BOOT</sub> pins.
8. To prevent overvoltage on the V<sub>CC</sub> pins, a Zener diode (D<sub>Z1</sub>) can be used. Similarly, on the V<sub>BOOT</sub> pins, a Zener diode (D<sub>Z2</sub>) can be placed in parallel with each C<sub>BOOT</sub>.
9. The use of the decoupling capacitor C<sub>5</sub> (100 to 220 nF, with low ESR and low ESL) in parallel with the electrolytic capacitor C<sub>BUS</sub> is useful to prevent surge destruction. Both capacitors C<sub>5</sub> and C<sub>BUS</sub> should be placed as close as possible to the IPM (C<sub>5</sub> has priority over C<sub>BUS</sub>).
10. When the application requires a galvanic isolation between low and high voltage, use of high speed (high CMR) opto-coupler is recommended.
11. Low inductance shunt resistors should be used for phase leg current sensing.
12. In order to avoid malfunction, the wiring between N pins, the shunt resistor and PWR\_GND should be as short as possible.
13. The connection of SGN\_GND to PWR\_GND at only one point (close to the shunt resistor terminal) can help to reduce the impact of power ground fluctuation.
14. Parallel connection of switches or legs on the same or multiple IPMs is not suggested.

These guidelines ensure the device specifications for application designs. For further details, please refer to the relevant application note.

**Table 12. Recommended operating conditions**

| Symbol            | Parameter                          | Test conditions                                                         | Min. | Typ. | Max. | Unit |
|-------------------|------------------------------------|-------------------------------------------------------------------------|------|------|------|------|
| V <sub>PN</sub>   | Supply voltage                     | Applied between P-Nu, N <sub>V</sub> , N <sub>W</sub>                   |      | 300  | 400  | V    |
| V <sub>CCHx</sub> | Control supply voltage             | Applied between V <sub>CCHx</sub> -GND                                  | 13.5 | 15   | 16.5 | V    |
| V <sub>CCL</sub>  | Control supply voltage             | Applied between V <sub>CCL</sub> -GND                                   | 13.5 | 15   | 16.5 | V    |
| V <sub>BS</sub>   | High-side bias voltage             | Applied between V <sub>BOOTi</sub> -OUT <sub>i</sub><br>for i = U, V, W | 13   | 15   | 18.5 | V    |
| t <sub>dead</sub> | Blanking time to prevent arm-short | For each input signal                                                   | 1.5  |      |      | μs   |
| f <sub>PWM</sub>  | PWM input signal                   | -40 °C < T <sub>C</sub> < 100 °C<br>-40 °C < T <sub>J</sub> < 125 °C    |      |      | 20   | kHz  |
| T <sub>C</sub>    | Case operation temperature         |                                                                         |      |      | 125  | °C   |

## 7 Electrical characteristics (curves)







**Figure 11. Output characteristics**

**Figure 12.  $V_{CE(sat)}$  vs collector current**

**Figure 13.  $I_C$  vs case temperature**

**Figure 14. Diode  $V_F$  vs forward current**

**Figure 15.  $E_{on}$  switching energy vs collector current**

**Figure 16.  $E_{off}$  switching energy vs collector current**


**Figure 17. Normalized thermal impedance for IGBT**





**Figure 18. Normalized thermal impedance for FRD**




## 8 Package information

In order to meet environmental requirements, ST offers these devices in different grades of **ECOPACK** packages, depending on their level of environmental compliance. ECOPACK specifications, grade definitions and product status are available at: [www.st.com](http://www.st.com). ECOPACK is an ST trademark.

### 8.1 SDIPHP-30L package information

**Figure 19. SDIPHP-30L package outline and mechanical data (dimensions are in mm)**



DM00727478\_1

## Revision history

**Table 13. Document revision history**

| Date        | Revision | Changes                                                                   |
|-------------|----------|---------------------------------------------------------------------------|
| 23-Sep-2021 | 1        | First release.                                                            |
| 15-Dec-2023 | 2        | Updated <a href="#">Table 1</a> . Pin description.<br>Minor text changes. |

## Contents

|          |                                               |           |
|----------|-----------------------------------------------|-----------|
| <b>1</b> | <b>Internal schematic and pin description</b> | <b>2</b>  |
| <b>2</b> | <b>Absolute maximum ratings</b>               | <b>4</b>  |
| <b>3</b> | <b>Electrical characteristics</b>             | <b>6</b>  |
| 3.1      | Inverter parts                                | 6         |
| 3.2      | Control/protection parts                      | 8         |
| <b>4</b> | <b>Bootstrap diode</b>                        | <b>11</b> |
| <b>5</b> | <b>NTC thermistor</b>                         | <b>12</b> |
| <b>6</b> | <b>Application circuit example</b>            | <b>13</b> |
| 6.1      | Guidelines                                    | 14        |
| <b>7</b> | <b>Electrical characteristics (curves)</b>    | <b>15</b> |
| <b>8</b> | <b>Package information</b>                    | <b>17</b> |
| 8.1      | SDIPHP-30L package information                | 17        |
|          | <b>Revision history</b>                       | <b>18</b> |

**IMPORTANT NOTICE – READ CAREFULLY**

STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, enhancements, modifications, and improvements to ST products and/or to this document at any time without notice. Purchasers should obtain the latest relevant information on ST products before placing orders. ST products are sold pursuant to ST's terms and conditions of sale in place at the time of order acknowledgment.

Purchasers are solely responsible for the choice, selection, and use of ST products and ST assumes no liability for application assistance or the design of purchasers' products.

No license, express or implied, to any intellectual property right is granted by ST herein.

Resale of ST products with provisions different from the information set forth herein shall void any warranty granted by ST for such product.

ST and the ST logo are trademarks of ST. For additional information about ST trademarks, refer to [www.st.com/trademarks](http://www.st.com/trademarks). All other product or service names are the property of their respective owners.

Information in this document supersedes and replaces information previously supplied in any prior versions of this document.

© 2023 STMicroelectronics – All rights reserved