
2SA0777 (2SA777)

Silicon PNP epitaxial planar type

For low-frequency driver amplification
Complementary to 2SC1509



■ Features

- High collector-emitter voltage (Base open) V_{CEO}
- Optimum for the driver stage of a low-frequency and 25 W to 30 W output amplifier.

■ Absolute Maximum Ratings $T_a = 25°C$

Parameter	Symbol	Rating	Unit
Collector-base voltage (Emitter open)	V_{CBO}	−80	V
Collector-emitter voltage (Base open)	V_{CEO}	−80	V
Emitter-base voltage (Collector open)	V_{EBO}	−5	V
Collector current	I_C	− 0.5	A
Peak collector current	I_{CP}	−1	A
Collector power dissipation	P_C	1	W
Junction temperature	T_j	150	°C
Storage temperature	T_{stg}	−55 to +150	°C

■ Electrical Characteristics $T_a = 25°C \pm 3°C$

Parameter	Symbol	Conditions	Min	Typ	Max	Unit
Collector-base voltage (Emitter open)	V_{CBO}	$I_C = -10$ µA, $I_E = 0$	−80			V
Collector-emitter voltage (Base open)	V_{CEO}	$I_C = -100$ µA, $I_B = 0$	−80			V
Emitter-base voltage (Collector open)	V_{EBO}	$I_E = -1$ µA, $I_C = 0$	−5			V
Collector-base cutoff current (Emitter open)	I_{CBO}	$V_{CB} = -20$ V, $I_E = 0$			− 0.1	µA
Forward current transfer ratio *1	h_{FE1} *2	$V_{CE} = -10$ V, $I_C = -150$ mA	90		220	—
	h_{FE2}	$V_{CE} = -5$ V, $I_C = -500$ mA	50	100		
Collector-emitter saturation voltage	$V_{CE(sat)}$	$I_C = -500$ mA, $I_B = -50$ mA		− 0.2	− 0.4	V
Base-emitter saturation voltage	$V_{BE(sat)}$	$I_C = -500$ mA, $I_B = -50$ mA		− 0.85	−1.2	V
Transition frequency	f_T	$V_{CB} = -10$ V, $I_E = 50$ mA, f = 200 MHz		120		MHz
Collector output capacitance (Common base, input open circuited)	C_{ob}	$V_{CB} = -10$ V, $I_E = 0$, f = 1 MHz		11	20	pF

Note) 1. Measuring methods are based on JAPANESE INDUSTRIAL STANDARD JIS C 7030 measuring methods for transistors.
2. ∗1: Palse measurement
∗2: Rank classification


Rank	Q	R
h_{FE1}	90 to 155	130 to 220

Note) The part number in the parenthesis shows conventional part number.


Maintenance/ Discontinued

Maintenance includes following four Product lifecycle stage.
Planned maintenance type
Maintenance type
Planned discontinued typed
Discontinued type
Please refer following URL about latest information.
http://industrial.panasonic.com/ac/e/semicon/transistor/index.jsp


P_C — T_a




I_C — V_{CE}




I_C — I_B




$V_{CE(sat)}$ — I_C




$V_{BE(sat)}$ — I_C




h_{FE} — I_C




f_T — I_E



C_{ob} — V_{CB}




I_{CBO} — T_a




Maintenance/Discontinued
Please visit the following URL about this and alternative models.
http://www.semicon.panasonic.co.jp/en/
Planned discontinued type
Please visit the following URL about this and alternative models.
http://www.semicon.panasonic.co.jp/en/
Maintenance/Discontinued
Discontinued
Maintenance/Discontinued

I_{CEO} — T_a



Safe operation area



Maintenance/Discontinued
Maintenance/Discontinued includes following four Product lifecycle stage.
planed maintenance type
maintenance type
planed discontinued typed
discontinued type
Please visit following URL about latest information.
http://www.semicon.panasonic.co.jp/en/

Request for your special attention and precautions in using the technical information and semiconductors described in this book

(1) If any of the products or technical information described in this book is to be exported or provided to non-residents, the laws and regulations of the exporting country, especially, those with regard to security export control, must be observed.

(2) The technical information described in this book is intended only to show the main characteristics and application circuit examples of the products, and no license is granted under any intellectual property right or other right owned by our company or any other company. Therefore, no responsibility is assumed by our company as to the infringement upon any such right owned by any other company which may arise as a result of the use of technical information described in this book.

(3) The products described in this book are intended to be used for standard applications or general electronic equipment (such as office equipment, communications equipment, measuring instruments and household appliances).
Consult our sales staff in advance for information on the following applications:
- Special applications (such as for airplanes, aerospace, automobiles, traffic control equipment, combustion equipment, life support systems and safety devices) in which exceptional quality and reliability are required, or if the failure or malfunction of the products may directly jeopardize life or harm the human body.
- Any applications other than the standard applications intended.

(4) The products and product specifications described in this book are subject to change without notice for modification and/or improvement. At the final stage of your design, purchasing, or use of the products, therefore, ask for the most up-to-date Product Standards in advance to make sure that the latest specifications satisfy your requirements.

(5) When designing your equipment, comply with the range of absolute maximum rating and the guaranteed operating conditions (operating power supply voltage and operating environment etc.). Especially, please be careful not to exceed the range of absolute maximum rating on the transient state, such as power-on, power-off and mode-switching. Otherwise, we will not be liable for any defect which may arise later in your equipment.
Even when the products are used within the guaranteed values, take into the consideration of incidence of break down and failure mode, possible to occur to semiconductor products. Measures on the systems such as redundant design, arresting the spread of fire or preventing glitch are recommended in order to prevent physical injury, fire, social damages, for example, by using the products.

(6) Comply with the instructions for use in order to prevent breakdown and characteristics change due to external factors (ESD, EOS, thermal stress and mechanical stress) at the time of handling, mounting or at customer's process. When using products for which damp-proof packing is required, satisfy the conditions, such as shelf life and the elapsed time since first opening the packages.

(7) This book may be not reprinted or reproduced whether wholly or partially, without the prior written permission of Matsushita Electric Industrial Co., Ltd.

Maintenance/Discontinued
Maintenance/Discontinued includes following our product's life cycle stage.
planed maintenance type
maintenance type
planed discontinued type
discontinued type
Please visit following URL about latest information.
http://www.semicon.panasonic.co.jp/en/