
NPN Silicon AF Transistor

- For general AF applications
- High collector current
- High current gain
- Low collector-emitter saturation voltage
- Pb-free (RoHS compliant) package
- Qualified according AEC Q101



Type	Marking	Pin Configuration						Package
BC817K-16	6As	1 = B	2 = E	3 = C	-	-	-	SOT23
BC817K-16W	6As	1 = B	2 = E	3 = C	-	-	-	SOT323
BC817K-25	6Bs	1 = B	2 = E	3 = C	-	-	-	SOT23
BC817K-25W	6Bs	1 = B	2 = E	3 = C	-	-	-	SOT323
BC817K-40	6Cs	1 = B	2 = E	3 = C	-	-	-	SOT23
BC817K-40W	6Cs	1 = B	2 = E	3 = C	-	-	-	SOT323
BC818K-16W	6Es	1 = B	2 = E	3 = C	-	-	-	SOT323
BC818K-40	6Gs	1 = B	2 = E	3 = C	-	-	-	SOT23

Maximum Ratings

Parameter	Symbol	Value	Unit
Collector-emitter voltage	V_{CEO}		V
BC817...		45	
BC818...		25	
Collector-base voltage	V_{CBO}		
BC817...		50	
BC818...		30	
Emitter-base voltage	V_{EBO}	5	
Collector current	I_C	500	mA
Peak collector current	I_{CM}	1000	
Base current	I_B	100	
Peak base current	I_{BM}	200	
Total power dissipation-	P_{tot}		mW
$T_S \leq 115$ °C, BC817K, BC818K		500	
$T_S \leq 130$ °C, BC817KW, BC818KW		250	
Junction temperature	T_j	150	°C
Storage temperature	T_{stg}	-65 ... 150	

Thermal Resistance

Parameter	Symbol	Value	Unit
Junction - soldering point[1)]	R_{thJS}		K/W
BC817K, BC818K		≤ 70	
BC817KW, BC818KW		≤ 80	

[1]For calculation of R_{thJA} please refer to Application Note AN077 (Thermal Resistance Calculation)

Electrical Characteristics at T_A = 25°C, unless otherwise specified

Parameter	Symbol	Values			Unit
		min.	typ.	max.	
DC Characteristics					
Collector-emitter breakdown voltage	$V_{(BR)CEO}$				V
I_C = 10 mA, I_B = 0 , BC817...		45	-	-	
I_C = 10 mA, I_B = 0 , BC818...		25	-	-	
Collector-base breakdown voltage	$V_{(BR)CBO}$				-
I_C = 10 µA, I_E = 0 , BC817...		50	-	-	
I_C = 10 µA, I_E = 0 , BC818...		30	-	-	
Emitter-base breakdown voltage	$V_{(BR)EBO}$	5	-	-	V
I_E = 10 µA, I_C = 0					
Collector-base cutoff current	I_{CBO}				µA
V_{CB} = 25 V, I_E = 0		-	-	0.1	
V_{CB} = 25 V, I_E = 0 , T_A = 150 °C		-	-	50	
Emitter-base cutoff current	I_{EBO}	-	-	100	nA
V_{EB} = 4 V, I_C = 0					
DC current gain[1)]	h_{FE}				-
I_C = 100 mA, V_{CE} = 1 V, h_{FE}-grp.16		100	160	250	
I_C = 100 mA, V_{CE} = 1 V, h_{FE}-grp.25		160	250	400	
I_C = 100 mA, V_{CE} = 1 V, h_{FE}-grp.40		250	350	630	
I_C = 500 mA, V_{CE} = 1 V, all h_{FE}-grps.		40	-	-	
Collector-emitter saturation voltage[1)]	V_{CEsat}	-	-	0.7	V
I_C = 500 mA, I_B = 50 mA					
Base emitter saturation voltage[1)]	V_{BEsat}	-	-	1.2	
I_C = 500 mA, I_B = 50 mA					

[1]Pulse test: t < 300µs; D < 2%


Electrical Characteristics at T_A = 25°C, unless otherwise specified

Parameter	Symbol	Values			Unit
		min.	typ.	max.	
AC Characteristics					
Transition frequency I_C = 50 mA, V_{CE} = 5 V, f = 100 MHz	f_T	-	170	-	MHz
Collector-base capacitance V_{CB} = 10 V, f = 1 MHz	C_{cb}	-	3	-	pF
Emitter-base capacitance V_{EB} = 0.5 V, f = 1 MHz	C_{eb}	-	40	-	

DC current gain $h_{FE} = f(I_C)$

V_{CE} = 1 V


h_{FE}-grp.16



DC current gain $h_{FE} = f(I_C)$

V_{CE} = 1 V


h_{FE}-grp.25



DC current gain $h_{FE} = f(I_C)$


V_{CE} = 1 V

h_{FE}-grp.40




Collector-emitter saturation voltage

$I_C = f(V_{CEsat})$, h_{FE} = 10




Base-emitter saturation voltage

$I_C = f(V_{BEsat})$, $h_{FE} = 10$




Collector cutoff current $I_{CBO} = f(T_A)$

V_{CBO} = 25 V



Transition frequency $f_T = f(I_C)$


V_{CE} = parameter in V, f = 2 GHz




Collector-base capacitance $C_{cb} = f(V_{CB})$

Emitter-base capacitance $C_{eb} = f(V_{EB})$


BC817K, BC818K




Total power dissipation $P_{tot} = f(T_S)$
BC817K, BC818K




Total power dissipation $P_{tot} = f(T_S)$
BC817KW, BC818KW



Permissible Pulse Load $R_{thJS} = f(t_p)$
BC817K, BC818K




Permissible Pulse Load
$P_{totmax}/P_{totDC} = f(t_p)$
BC817K, BC818K



Permissible Puls Load $R_{thJS} = f(t_p)$


BC817KW, BC818KW



Permissible Pulse Load


$P_{totmax}/P_{totDC} = f(t_p)$

BC817KW, BC818KW




Package Outline






1) Lead width can be 0.6 max. in dambar area

Foot Print




Marking Layout (Example)




Standard Packing

Reel ø180 mm = 3.000 Pieces/Reel
Reel ø330 mm = 10.000 Pieces/Reel




Package Outline






Foot Print




Marking Layout (Example)



Standard Packing

Reel ø180 mm = 3.000 Pieces/Reel
Reel ø330 mm = 10.000 Pieces/Reel



Edition 2009-11-16

Published by
Infineon Technologies AG
81726 Munich, Germany

© 2009 Infineon Technologies AG
All Rights Reserved.

Legal Disclaimer

The information given in this document shall in no event be regarded as a guarantee of conditions or characteristics. With respect to any examples or hints given herein, any typical values stated herein and/or any information regarding the application of the device, Infineon Technologies hereby disclaims any and all warranties and liabilities of any kind, including without limitation, warranties of non-infringement of intellectual property rights of any third party.

Information

For further information on technology, delivery terms and conditions and prices, please contact the nearest Infineon Technologies Office (<www.infineon.com>).

Warnings

Due to technical requirements, components may contain dangerous substances. For information on the types in question, please contact the nearest Infineon Technologies Office.
Infineon Technologies components may be used in life-support devices or systems only with the express written approval of Infineon Technologies, if a failure of such components can reasonably be expected to cause the failure of that life-support device or system or to affect the safety or effectiveness of that device or system. Life support devices or systems are intended to be implanted in the human body or to support and/or maintain and sustain and/or protect human life. If they fail, it is reasonable to assume that the health of the user or other persons may be endangered.