Data Sheet | Item Number: 870-405

Jumper; 5-way; insulated; light gray

https://www.wago.com/870-405



Color: light gray

Technical data	
Number of spacings	5 -times

Electrical data	
Rated current	18 A

Physical data	
Width	24 mm / 0.945 inches
Height	2.5 mm / 0.098 inches

Material data	
Color	light gray
Fire load	0.019 MJ
Weight	2.2 g

Commercial data	
Product Group	16 (Rail Mounted Terminal Blocks with CCC)
PU (SPU)	25 (25) pcs
Packaging type	Bag
Country of origin	DE
GTIN	4066966271737
Customs tariff number	85366990990

Product Classification

UNSPSC	39121421
eCl@ss 10.0	27-14-11-40
eCl@ss 9.0	27-14-11-40
ETIM 9.0	EC000489
ETIM 10.0	EC000489
ECCN	NO US CLASSIFICATION

Environmental Product Compliance

RoHS Compliance Status	Compliant,No Exemption

Downloads

Environmental Product Compliance

Compliance Search

Environmental Product Compliance 870-405

Documentation

Bid Text

870-405	19.02.2019	xml 2.51 KB	
870-405	04.01.2018	doc 23.50 KB	

CAD/CAE-Data

CAD data

2D/3D Models 870-405

CAE data

EPLAN Data Portal 870-405

WSCAD Universe 870-405

ZUKEN Portal 870-405

Installation Notes

Continued on next page

Commoning



Insert push-in type jumper bar and push down until it hits backstop.



Removing a push-in type jumper bar:
Insert the operating tool between the jumper and partition wall of the dual jumper slots, then lift up the jumper.
Place the operating tool in the center of jumpers for up to five contacts (see above), or alternately on both sides for jumpers with more than five contacts.

Commoning



Custom jumpers are created by breaking and removing jumper contacts (2000, 2001, 2002, 2004 Series).




Marking with a felt-tip pen.

Commoning



Stepping down via push-in type jumper bar.



Stepping down via push-in type jumper bar:
Commoning via closed terminal side with end plate allows jumpering over two cross-section sizes, e.g., from 16 mm² (6 AWG) to 6 mm² (10 AWG) or from 6 mm² (10 AWG) to 2.5 mm² (14 AWG) (see illustration above).



Stepping down via push-in type jumper bar:
Commoning via open terminal side with end plate allows jumpering over two cross-section sizes for 16 mm² (6 AWG) and 10 mm² (8 AWG) and one cross-section size for 6/4/2.5 mm² (10/12/14 AWG). An example: from 16 mm² (6 AWG) to 6 mm² (10 AWG) (see illustration above) or from 10 mm² (8 AWG) to 4 mm² (12 AWG).



Note:
The total current of the outgoing circuits must not exceed the nominal current of the step-down jumper/push-in type jumper bar.