Ordering number:EN2931A

SB10-05A2, SB10-05A3

Schottky Barrier Diode

50V, 1.0A Rectifier

Applications

· High frequency rectification (switching regulators, converters, choppers).

Features


· Low forward voltage (V_F max=0.58V).
· Fast reverse recovery time (trr max=30ns).
· Low switching noise.
· Average rectified current (I_O=1.0A).

Package Dimensions

unit:mm

1208

[SB10-05A2]




C:Cathode
A:Anode

unit:mm

1209

[SB10-05A3]



C:Cathode
A:Anode

Specifications

Absolute Maximum Ratings at Ta = 25˚C

Parameter	Symbol	Conditions		Ratings	Unit
Repetitive Peak Reverse Voltage	V_{RRM}			50	V
Nonrepetitive Peak Reverse Surge Voltage	V_{RSM}			55	V
Average Rectified Current	I_O	SB10-05A2	50Hz, resistive load, sine wave, Ta=33˚C (L=8mm, 10×10mm² print land)	1.0	A
		SB10-05A3	50Hz, resistive load, sine wave, Ta=29˚C (L=3mm, 5×5mm² print land)	1.0	A
Surge Forward Current	I_{FSM}	50Hz sine wave, 1 cycle		25	A
Junction Temperature	Tj			125	˚C
Storage Temperature	Tstg			–40 to +125	˚C


Electrical Characteristics at Ta = 25˚C

Parameter	Symbol	Conditons	Ratings			Unit
			min	typ	max	
Forward Voltage	V_F	I_F=1.0A			0.58	V
Reverse Current	I_R	V_R=50V			1.0	mA
Reverse Recovery Time	trr	I_{FM}=1A, $-dI_F/dt$=50A/μs			30	ns
Thermal Resistance (Junction-Ambient)	Rth(j-a)	No fin, device only			140	˚C/W


SANYO Electric Co.,Ltd. Semiconductor Bussiness Headquaters
TOKYO OFFICE Tokyo Bldg., 1-10, 1 Chome, Ueno, Taito-ku, TOKYO, 110-8534 JAPAN

Downloaded from Arrow.com.


$I_O - T_a$




$I_O - T_a$




$I_F - V_F$




$I_R - V_R$




$P_F - I_O$




$P_R - V_R$



$I_{FSM} - n$



$C - V_R$



Downloaded from Arrow.com.

■ No products described or contained herein are intended for use in surgical implants, life-support systems, aerospace equipment, nuclear power control systems, vehicles, disaster/crime-prevention equipment and the like, the failure of which may directly or indirectly cause injury, death or property loss.

■ Anyone purchasing any products described or contained herein for an above-mentioned use shall:

① Accept full responsibility and indemnify and defend SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors and all their officers and employees, jointly and severally, against any and all claims and litigation and all damages, cost and expenses associated with such use:

② Not impose any responsibilty for any fault or negligence which may be cited in any such claim or litigation on SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors or any of their officers and employees jointly or severally.

■ Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.

This catalog provides information as of April, 1998. Specifications and information herein are subject to change without notice.

Downloaded from Arrow.com.